

**CEN**

**CWA 14050-4**

**WORKSHOP**

October 2003

**AGREEMENT**

---

ICS 35.200; 35.240.15

Supersedes CWA 14050-4:2000

English version

**Extensions for Financial Services (XFS) interface specification -  
Release 3.0 - Part 4: Identification Card Device Class Interface -  
Programmer's Reference**

This CEN Workshop Agreement has been drafted and approved by a Workshop of representatives of interested parties, the constitution of which is indicated in the foreword of this Workshop Agreement.

The formal process followed by the Workshop in the development of this Workshop Agreement has been endorsed by the National Members of CEN but neither the National Members of CEN nor the CEN Management Centre can be held accountable for the technical content of this CEN Workshop Agreement or possible conflicts with standards or legislation.

This CEN Workshop Agreement can in no way be held as being an official standard developed by CEN and its Members.

This CEN Workshop Agreement is publicly available as a reference document from the CEN Members National Standard Bodies.

CEN members are the national standards bodies of Austria, Belgium, Czech Republic, Denmark, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Luxembourg, Malta, Netherlands, Norway, Portugal, Slovakia, Spain, Sweden, Switzerland and United Kingdom.



EUROPEAN COMMITTEE FOR STANDARDIZATION  
COMITÉ EUROPÉEN DE NORMALISATION  
EUROPÄISCHES KOMITEE FÜR NORMUNG

**Management Centre: rue de Stassart, 36 B-1050 Brussels**

---

© 2003 CEN All rights of exploitation in any form and by any means reserved worldwide for CEN national Members.

Ref. No. CWA 14050-4:2003 D/E/F

## Table of Contents

---

Foreword .....	3
1. Introduction .....	5
1.1 Background to Release 3.02 .....	5
1.2 XFS Service-Specific Programming .....	5
2. Identification Card Readers and Writers .....	7
3. References .....	8
4. Info Commands .....	9
4.1 WFS_INF_IDC_STATUS .....	9
4.2 WFS_INF_IDC_CAPABILITIES .....	11
4.3 WFS_INF_IDC_FORM_LIST .....	13
4.4 WFS_INF_IDC_QUERY_FORM .....	14
5. Execute Commands .....	15
5.1 WFS_CMD_IDC_READ_TRACK .....	15
5.2 WFS_CMD_IDC_WRITE_TRACK .....	16
5.3 WFS_CMD_IDC_EJECT_CARD .....	18
5.4 WFS_CMD_IDC_RETAIN_CARD .....	18
5.5 WFS_CMD_IDC_RESET_COUNT .....	19
5.6 WFS_CMD_IDC_SETKEY .....	19
5.7 WFS_CMD_IDC_READ_RAW_DATA .....	20
5.8 WFS_CMD_IDC_WRITE_RAW_DATA .....	22
5.9 WFS_CMD_IDC_CHIP_IO .....	24
5.10 WFS_CMD_IDC_RESET .....	25
5.11 WFS_CMD_IDC_CHIP_POWER .....	25
5.12 WFS_CMD_IDC_PARSE_DATA .....	26
6. Events .....	28
6.1 WFS_EXEE_IDC_INVALIDTRACKDATA .....	28
6.2 WFS_EXEE_IDC_MEDIAINsertED .....	28
6.3 WFS_SRVE_IDC_MEDIAREMOVED .....	28
6.4 WFS_EXEE_IDC_MEDIARETAINED .....	28
6.5 WFS_EXEE_IDC_INVALIDMEDIA .....	28
6.6 WFS_SRVE_IDC_CARDACTION .....	29
6.7 WFS_USRE_IDC_RETAINBINThRESHOLD .....	29
6.8 WFS_SRVE_IDC_MEDIADETECTED .....	29
7. Form Description .....	30
8. Relation with PC/SC .....	33
9. C-Header file .....	34

## Foreword

---

This CWA is revision 3.02 of the XFS interface specification.

The CEN/ISSS XFS Workshop gathers suppliers as well as banks and other financial service companies. A list of companies participating in this Workshop and in support of this CWA is available from the CEN/ISSS Secretariat.

This document supersedes CWA 14050-4:2000.

This CWA was formally approved by the XFS Workshop meeting on 2003-05-21. The specification is continuously reviewed and commented in the CEN/ISSS Workshop on XFS. It is therefore expected that an update of the specification will be published in due time as a CWA, superseding this revision 3.02.

The CWA is published as a multi-part document, consisting of:

Part 1: Application Programming Interface (API) - Service Provider Interface (SPI); Programmer's Reference

Part 2: Service Classes Definition; Programmer's Reference

Part 3: Printer Device Class Interface - Programmer's Reference

Part 4: Identification Card Device Class Interface - Programmer's Reference

Part 5: Cash Dispenser Device Class Interface - Programmer's Reference

Part 6: PIN Keypad Device Class Interface - Programmer's Reference

Part 7: Check Reader/Scanner Device Class Interface - Programmer's Reference

Part 8: Depository Device Class Interface - Programmer's Reference

Part 9: Text Terminal Unit Device Class Interface - Programmer's Reference

Part 10: Sensors and Indicators Unit Device Class Interface - Programmer's Reference

Part 11: Vendor Dependent Mode Device Class Interface - Programmer's Reference

Part 12: Camera Device Class Interface - Programmer's Reference

Part 13: Alarm Device Class Interface - Programmer's Reference

Part 14: Card Embossing Unit Class Interface - Programmer's Reference

Part 15: Cash In Module Device Class Interface- Programmer's Reference

Part 16: Application Programming Interface (API) - Service Provider Interface (SPI) - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (this CWA) - Programmer's Reference

Part 17: Printer Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (this CWA) - Programmer's Reference

Part 18: Identification Card Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (see CWA 14050-4:2000; superseded) - Programmer's Reference

Part 19: Cash Dispenser Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (this CWA) - Programmer's Reference

Part 20: PIN Keypad Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (see CWA 14050-6:2000; superseded) - Programmer's Reference

Part 21: Depository Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (this CWA) - Programmer's Reference

Part 22: Text Terminal Unit Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (this CWA) - Programmer's Reference

Part 23: Sensors and Indicators Unit Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.01 (this CWA) - Programmer's Reference

Part 24: Camera Device Class Interface - Migration from Version 2.00 (see CWA 13449) to Version 3.00 (this CWA) - Programmer's Reference

## CWA 14050-4:2003 (E)

Part 25: Identification Card Device Class Interface - PC/SC Integration Guidelines

Part 26: Identification Card Device Class Interface - Migration from Version 3.00 (see CWA 14050-4:2000; superseded) to Version 3.02 (this CWA) - Programmer's Reference

Part 27: PIN Keypad Device Class Interface - Migration from Version 3.00 (see CWA 14050-6:2000; superseded) to Version 3.02 (this CWA) - Programmer's Reference

Part 28: Cash In Module Device Class Interface - Migration from Version 3.00 (see CWA 14050-15:2000; superseded) to Version 3.02 (this CWA) - Programmer's Reference

In addition to these Programmer's Reference specifications, the reader of this CWA is also referred to a complementary document, called Release Notes. The Release Notes contain clarifications and explanations on the CWA specifications, which are not requiring functional changes. The current version of the Release Notes is available online from <http://www.cenorm.be/iss/Workshop/XFS>.

The information in this document represents the Workshop's current views on the issues discussed as of the date of publication. It is furnished for informational purposes only and is subject to change without notice. CEN/ISSS makes no warranty, express or implied, with respect to this document.

### Revision History:

---

1.0	24 May 1993	Initial release of API and SPI specification
1.11	3 February 1995	Separation of specification into separate documents for API/SPI and service class definitions; with updates.
2.00	11 November 1996	Updated release encompassing self-service environment Chip Card handling inserted.
3.00	18 October 2000	<ul style="list-style-type: none"><li>• Eliminate reference to Registry as a form of implementation for threshold value in WFS_USRE_IDC_RETAINBINTHRESHOLD command.</li><li>• Clarify that Form Definition attributes are not required in any mandatory order.</li><li>• Clarify WFS_IDC_DEVBUSY meaning.</li><li>• Add WFS_CMD_IDC_RESET command.</li><li>• High Coercivity enhancements</li></ul>
		For a detailed description see CWA 14050-18: 2003 IDC migration from version 2.00 to version 3.00
3.02	21 May 2003	Updated to handle latching smart cards within a Smart/DIP device and devices with permanently connected chip cards.
		For a detailed description see CWA 14050-26: 2003 IDC migration from version 3.00 to version 3.02

## 1. Introduction

---

### 1.1 Background to Release 3.02

---

The CEN XFS Workshop is a continuation of the Banking Solution Vendors Council workshop and maintains a technical commitment to the Win 32 API. However, the XFS Workshop has extended the franchise of multi vendor software by encouraging the participation of both banks and vendors to take part in the deliberations of the creation of an industry standard. This move towards opening the participation beyond the BSVC's original membership has been very successful with a current membership level of more than 20 companies.

The fundamental aims of the XFS Workshop are to promote a clear and unambiguous specification for both service providers and application developers. This has been achieved to date by sub groups working electronically and quarterly meetings.

The move from an XFS 3.00 specification to a 3.02 specification has been prompted by a series of factors. There has been pressure from the market to fully support Smart/DIP card readers and card readers where there are chip cards which are permanently connected.

The clear direction of the XFS Workshop, therefore, is the delivery of a new Release 3.02 specification based on a C API. It will be delivered with the promise of the protection of technical investment for existing applications and the design to safeguard future developments. All XFS 3.00 IDC clarifications still apply to this document.

### 1.2 XFS Service-Specific Programming

---

The service classes are defined by their service-specific commands and the associated data structures, error codes, messages, etc. These commands are used to request functions that are specific to one or more classes of service providers, but not all of them, and therefore are not included in the common API for basic or administration functions.

When a service-specific command is common among two or more classes of service providers, the syntax of the command is as similar as possible across all services, since a major objective of the Extensions for Financial Services is to standardize function codes and structures for the broadest variety of services. For example, using the **WFSExecute** function, the commands to read data from various services are as similar as possible to each other in their syntax and data structures.

In general, the specific command set for a service class is defined as a superset of the specific capabilities likely to be provided by the developers of the services of that class; thus any particular device will normally support only a subset of the defined command set.

There are three cases in which a service provider may receive a service-specific command that it does not support:

- The requested capability is defined for the class of service providers by the XFS specification, the particular vendor implementation of that service does not support it, and the unsupported capability is *not* considered to be fundamental to the service. In this case, the service provider returns a successful completion, but does no operation. An example would be a request from an application to turn on a control indicator on a passbook printer; the service provider recognizes the command, but since the passbook printer it is managing does not include that indicator, the service provider does no operation and returns a successful completion to the application.
- The requested capability is defined for the class of service providers by the XFS specification, the particular vendor implementation of that service does not support it, and the unsupported capability *is* considered to be fundamental to the service. In this case, a `WFS_ERR_UNSUPP_COMMAND` error is returned to the calling application. An example would be a request from an application to a cash dispenser to dispense coins; the service provider recognizes the command but, since the cash dispenser it is managing dispenses only notes, returns this error.
- The requested capability is *not* defined for the class of service providers by the XFS specification. In this case, a `WFS_ERR_INVALID_COMMAND` error is returned to the calling application.

## **CWA 14050-4:2003 (E)**

This design allows implementation of applications that can be used with a range of services that provide differing subsets of the functionalities that are defined for their service class. Applications may use the **WFSGetInfo** and **WFSAsyncGetInfo** commands to inquire about the capabilities of the service they are about to use, and modify their behavior accordingly, or they may use functions and then deal with `WFS_ERR_UNSUPP_COMMAND` error returns to make decisions as to how to use the service.

## 2. Identification Card Readers and Writers

---

This section describes the functions provided by a generic identification card reader/writer service (IDC). These descriptions include definitions of the service-specific commands that can be issued, using the **WFSAsyncExecute**, **WFSExecute**, **WFSGetInfo** and **WFSAsyncGetInfo** functions.

This service allows for the operation of the following categories of units:

- motor driven card reader/writer
- pull through card reader (writing facilities only partially included)
- dip reader
- contactless chip card readers
- permanent chip card readers ( each chip is accessed through a unique logical service )

The following tracks/chips and the corresponding international standards are taken into account in this document:

Track 1	ISO 7811
Track 2	ISO 7811
Track 3	ISO 7811 / ISO 4909
Watermark	Sweden
Chip (contacted)	ISO 7816
Chip (contactless)	ISO 10536.

National standards like Transac for France are not considered, but can be easily included via the forms mechanism (see Section 7, Form Definition).

In addition to the pure reading of the tracks mentioned above, security boxes can be used via this service to check the data of writable tracks for manipulation. These boxes (such as CIM or MM) are sensor-equipped devices that are able to check some other information on the card and compare it with the track data.

Persistent values are maintained through power failures, open sessions, close session and system resets.

When the service controls a permanently connected chip card, **WFS\_ERR\_UNSUPP\_COMMAND** will be returned to all commands except **WFS\_INF\_IDC\_STATUS**, **WFS\_INF\_IDC\_CAPABILITIES**, **WFS\_CMD\_IDC\_CHIP\_POWER**, **WFS\_CMD\_IDC\_CHP\_IO** and **WFS\_CMD\_IDC\_RESET**.

### **3. References**

---

---

- |  |
|--|
| <p>1. XFS Application Programming Interface (API)/Service Provider Interface (SPI), Programmer's Reference<br/>Revision 3.00, October 18, 2000</p> |
|--|



## 4. Info Commands

### 4.1 WFS\_INF\_IDC\_STATUS

**Description** This command reports the full range of information available, including the information that is provided either by the service provider or, if present, by any of the security modules. In addition to that, the number of cards retained is transmitted for motor driven card reader/writer (for devices of the other categories this number is always set to zero).

**Input Param** None.

**Output Param** LPWFSIDCSTATUS lpStatus;

```
typedef struct _wfs_idc_status
{
    WORD          fwDevice;
    WORD          fwMedia;
    WORD          fwRetainBin;
    WORD          fwSecurity;
    USHORT       usCards;
    WORD          fwChipPower;
    LPSTR        lpszExtra;
} WFSIDCSTATUS, * LPWFSIDCSTATUS;
```

#### *fwDevice*

Specifies the state of the ID card device as one of the following flags:

Value	Meaning
WFS_IDC_DEVONLINE	The device is present, powered on and online (i.e., operational, not busy processing a request and not in an error state).
WFS_IDC_DEVOFFLINE	The device is offline (e.g., the operator has taken the device offline by turning a switch or pulling out the device).
WFS_IDC_DEVPOWEROFF	The device is powered off or physically not connected.
WFS_IDC_DEVNODEVICE	There is no device intended to be there; e.g. this type of self service machine does not contain such a device or it is internally not configured.
WFS_IDC_DEVHWERROR	The device is present but inoperable due to a hardware fault that prevents it from being used.
WFS_IDC_DEVUSERERROR	The device is present but a person is preventing proper device operation. The application should suspend the device operation or remove the device from service until the service provider generates a device state change event indicating the condition of the device has changed e.g. the error is removed (WFS_IDC_DEVONLINE) or a permanent error condition has occurred (WFS_IDC_DEVHWERROR).
WFS_IDC_DEVBUSY	The device is busy and unable to process an Execute command at this time.

#### *fwMedia*

Specifies the state of the ID card unit as one of the following values:

Value	Meaning
WFS_IDC_MEDIAPRESENT	Media is present in the device, not in the entering position and not jammed. On the Latched DIP device, this indicates that the card is present in the device and the card is unlatched.
WFS_IDC_MEDIANOTPRESENT	Media is not present in the device and not at the entering position.
WFS_IDC_MEDIAJAMMED	Media is jammed in the device; operator intervention is required.
WFS_IDC_MEDIANOTSUPP	Capability to report media position is not supported by the device (e.g., a typical swipe reader).
WFS_IDC_MEDIAUNKNOWN	The media state cannot be determined with the device in its current state (e.g., the value of <i>fwDevice</i> is

	WFS_IDC_DEVNODEVICE, WFS_IDC_DEVPOWEROFF, WFS_IDC_DEVOFFLINE, or WFS_IDC_DEVHWERROR).
WFS_IDC_MEDIAENTERING	Media is at the entry/exit slot of a motorized device.
WFS_IDC_MEDIALATCHED	Media is present & latched in a Latched-DIP card unit. This means the card can be used for chip card dialog.

*fwRetainBin*

Specifies the state of the ID card unit retain bin as one of the following values:

Value	Meaning
WFS_IDC_RETAINBINOK	The retain bin of the ID card unit is not full.
WFS_IDC_RETAINNOTSUPP	The ID card unit does not support retain capability.
WFS_IDC_RETAINBINFULL	The retain bin of the ID card unit is full.
WFS_IDC_RETAINBINHIGH	The retain bin of the ID card unit is nearly full.

*fwSecurity*

Specifies the state of the security unit as one of the following values:

Value	Meaning
WFS_IDC_SECNOTSUPP	No security module is available.
WFS_IDC_SECNOTREADY	The security module is not ready to process cards.
WFS_IDC_SECOPEN	The security module is open and ready to process cards.

*usCards*

The number of cards retained; applicable only to motor driven ID card units for non-motorized card units this value is 0. This value is persistent it is reset to zero by the WFS\_CMD\_IDC\_RESET\_COUNT command.

*fwChipPower*

Specifies the state of the chip controlled by this service. Depending on the value of fwType within the WFS\_INF\_IDC\_CAPABILITIES structure, this can either be the chip on the currently inserted user card or the chip on a permanently connected chip card. The state of the chip is one of the following flags:

Value	Meaning
WFS_IDC_CHIPONLINE	The chip is present, powered on and online (i.e. operational, not busy processing a request and not in an error state).
WFS_IDC_CHIPPOWEREDOFF	The chip is present, but powered off (i.e. not contacted).
WFS_IDC_CHIPBUSY	The chip is present, powered on, and busy (unable to process an Execute command at this time).
WFS_IDC_CHIPNODEVICE	A card is currently present in the device, but has no chip.
WFS_IDC_CHIPHWERROR	The chip is present, but inoperable due to a hardware error that prevents it from being used (e.g. MUTE, if there is an unresponsive card in the reader).
WFS_IDC_CHIPNOCARD	There is no card in the device.
WFS_IDC_CHIPNOTSUPP	Capability to report the state of the chip is not supported by the ID card unit device.
WFS_IDC_CHIPUNKNOWN	The state of the chip cannot be determined with the device in its current state.

*lpszExtra*

Points to a list of vendor-specific, or any other extended, information. The information is returned as a series of "key=value" strings so that it is easily extensible by service providers. Each string is null-terminated, with the final string terminating with two null characters.

**Error Codes**

Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Comments**

Applications which require or expect specific information to be present in the *lpszExtra* parameter may not be device or vendor-independent.

## 4.2 WFS\_INF\_IDC\_CAPABILITIES

---

**Description** This command is used to retrieve the capabilities of the ID card unit.

**Input Param** None.

**Output Param** LPWFSIDCCAPS lpCaps;

```
typedef struct _wfs_idc_caps
{
    WORD        wClass;
    WORD        fwType;
    BOOL        bCompound;
    WORD        fwReadTracks;
    WORD        fwWriteTracks;
    WORD        fwChipProtocols;
    USHORT     usCards;
    WORD        fwSecType;
    WORD        fwPowerOnOption;
    WORD        fwPowerOffOption;
    BOOL        bFluxSensorProgrammable;
    BOOL        bReadWriteAccessFollowingEject;
    WORD        fwWriteMode;
    WORD        fwChipPower;
    LPSTR      lpszExtra;
} WFSIDCCAPS, * LPWFSIDCCAPS;
```

*wClass*

Specifies the logical service class; value is WFS\_SERVICE\_CLASS\_IDC.

*fwType*

Specifies the type of the ID card unit as one of the following values:

Value	Meaning
WFS_IDC_TYEMOTOR	The ID card unit is a motor driven card unit.
WFS_IDC_TYEPWIPE	The ID card unit is a swipe (pull-through) card unit .
WFS_IDC_TYEPDIP	The ID card unit is a dip card unit. This DIP type is not capable of latching cards entered.
WFS_IDC_TYPECONTACTLESS	The ID card unit is a contactless card unit, i.e. no insertion of the card is required.
WFS_IDC_TYPELATCHEDDIP	The ID card unit is a latched dip card unit. This device type is used when a DIP IDC device supports chip communication. The latch ensures the consumer cannot remove the card during chip communication. Any card entered will automatically latch when a request to initiate a chip dialog is made (via the WFS_CMD_IDC_READ_RAW_DATA). The WFS_CMD_IDC_EJECT_CARD command is used to unlatch the card.
WFS_IDC_TYPEPERMANENT	The ID card unit is dedicated to a permanently housed chip card (no user interaction is available with this type of card).

*bCompound*

Specifies whether the logical device is part of a compound physical device and is either TRUE or FALSE.

*fwReadTracks*

Specifies the tracks that can be read by the ID card unit as a combination of the following flags:

Value	Meaning
WFS_IDC_NOTSUPP	The ID card unit can not access any track.
WFS_IDC_TRACK1	The ID card unit can access track 1.
WFS_IDC_TRACK2	The ID card unit can access track 2.
WFS_IDC_TRACK3	The ID card unit can access track 3.
WFS_IDC_TRACK_WM	The ID card unit can access the Swedish Watermark track.

## CWA 14050-4:2003 (E)

### *fwWriteTracks*

Specifies the tracks that can be written by the ID card unit (as a combination of the flags specified in the description of *fwReadTracks* except *WFS\_IDC\_TRACK\_WM*).

### *fwChipProtocols*

Specifies the chip card protocols that are supported by the service provider as a combination of the following flags:

Value	Meaning
WFS_IDC_NOTSUPP	The ID card unit can not handle chip cards.
WFS_IDC_CHIPT0	The ID card unit can handle the T=0 protocol.
WFS_IDC_CHIPT1	The ID card unit can handle the T=1 protocol.
WFS_IDC_CHIPT2	The ID card unit can handle the T=2 protocol.
WFS_IDC_CHIPT3	The ID card unit can handle the T=3 protocol.
WFS_IDC_CHIPT4	The ID card unit can handle the T=4 protocol.
WFS_IDC_CHIPT5	The ID card unit can handle the T=5 protocol.
WFS_IDC_CHIPT6	The ID card unit can handle the T=6 protocol.
WFS_IDC_CHIPT7	The ID card unit can handle the T=7 protocol.
WFS_IDC_CHIPT8	The ID card unit can handle the T=8 protocol.
WFS_IDC_CHIPT9	The ID card unit can handle the T=9 protocol.
WFS_IDC_CHIPT10	The ID card unit can handle the T=10 protocol.
WFS_IDC_CHIPT11	The ID card unit can handle the T=11 protocol.
WFS_IDC_CHIPT12	The ID card unit can handle the T=12 protocol.
WFS_IDC_CHIPT13	The ID card unit can handle the T=13 protocol.
WFS_IDC_CHIPT14	The ID card unit can handle the T=14 protocol.
WFS_IDC_CHIPT15	The ID card unit can handle the T=15 protocol.

### *usCards*

Specifies the maximum numbers of cards that the retain bin can hold (zero if not available).

### *fwSecType*

Specifies the type of security module used as one of the following values:

Value	Meaning
WFS_IDC_SECNOTSUPP	Device has no security module.
WFS_IDC_SECMBOX	Security module of device is MMBBox.
WFS_IDC_SECCIM86	Security module of device is CIM86.

### *fwPowerOnOption*

Specifies the power-on capabilities of the device hardware as one of the following values (applicable only to motor driven ID card units):

Value	Meaning
WFS_IDC_NOACTION	No power on actions are supported by the device
WFS_IDC_EJECT	The card will be ejected on power-on (or off, see <i>fwPowerOffOption</i> below).
WFS_IDC_RETAIN	The card will be retained on power-on (off).
WFS_IDC_EJECTTHENRETAIN	The card will be ejected for a specified time on power-on (off), then retained if not taken. The time for which the card is ejected is vendor dependent.
WFS_IDC_READPOSITION	The card will be moved into the read position on power-on (off).

### *fwPowerOffOption*

Specifies the power-off capabilities of the device hardware, as one of the flags specified for *fwPowerOnOption*; applicable only to motor driven ID card units.

### *bFluxSensorProgrammable*

Specifies whether the Flux Sensor on the card unit is programmable, this can either be TRUE or FALSE.

### *bReadWriteAccessFollowingEject*

Specifies whether a card may be read or written after having been pushed to the exit slot with an eject command. The card will be retracted back into the IDC.

### *fwWriteMode*

A combination of the following flags specify the write capabilities, with respect to whether the device can write low coercivity (loco) and/or high coercivity (hico) magnetic stripes:

Value	Meaning
WFS_IDC_NOTSUPP	Does not support writing of magnetic stripes.
WFS_IDC_LOCO	Supports writing of loco magnetic stripes.
WFS_IDC_HICO	Supports writing of hico magnetic stripes.
WFS_IDC_AUTO	Service provider is capable of automatically determining whether loco or hico magnetic stripes should be written.

*fwChipPower*

Specifies the capabilities of the ID card unit (in relation to the user or permanent chip controlled by the service), for chip power management as a combination of the following flags :

Value	Meaning
WFS_IDC_NOTSUPP	The ID card unit can not handle chip power management.
WFS_IDC_CHIPPOWERCOLD	The ID card unit can power on the chip and reset it (Cold Reset).
WFS_IDC_CHIPPOWERWARM	The ID card unit can reset the chip (Warm Reset).
WFS_IDC_CHIPPOWEROFF	The ID card unit can power off the chip.

*lpzExtra*

Points to a list of vendor-specific, or any other extended information. The information is returned as a series of "key=value" strings so that it is easily extensible by service providers. Each string is null-terminated, with the final string terminating with two null characters.

<b>Error Codes</b>	Only the generic error codes defined in [Ref. 1] can be generated by this command.
<b>Comments</b>	Applications which require or expect specific information to be present in the <i>lpzExtra</i> parameter may not be device or vendor-independent.

### 4.3 WFS\_INF\_IDC\_FORM\_LIST

---

<b>Description</b>	This command is used to retrieve the list of forms available on the device.
<b>Input Param</b>	None.
<b>Output Param</b>	LPSTR <i>lpzFormList</i> ;
	<i>lpzFormList</i> Pointer to a list of null-terminated form names, with the final name terminating with two null characters.
<b>Error Codes</b>	Only the generic error codes defined in [Ref. 1] can be generated by this command.
<b>Comments</b>	None.

## CWA 14050-4:2003 (E)

### 4.4 WFS\_INF\_IDC\_QUERY\_FORM

---

**Description** This command is used to retrieve details of the definition of a specified form.

**Input Param** LPSTR lpszFormName;

*lpszFormName*

Points to the null-terminated form name on which to retrieve details.

**Output Param** LPWFSIDCFORM lpForm;

```
typedef struct _wfs_idc_form
{
    LPSTR    lpszFormName;
    char     cFieldSeparatorTrack1;
    char     cFieldSeparatorTrack2;
    char     cFieldSeparatorTrack3;
    WORD     fwAction;
    LPSTR    lpszTracks;
    BOOL     bSecure;
    LPSTR    lpszTrack1Fields;
    LPSTR    lpszTrack2Fields;
    LPSTR    lpszTrack3Fields;
} WFSIDCFORM, * LPWFSIDCFORM;
```

*lpszFormName*

Specifies the null-terminated name of the form.

*cFieldSeparatorTrack1*

Specifies the value of the field separator of Track 1.

*cFieldSeparatorTrack2*

Specifies the value of the field separator of Track 2.

*cFieldSeparatorTrack3*

Specifies the value of the field separator of Track 3.

*fwAction*

Specifies the form action; can be one of the following flags:

Value	Meaning
WFS_IDC_ACTIONREAD	The form reads the card.
WFS_IDC_ACTIONWRITE	The form writes the card.

*lpszTracks*

Specifies the read algorithm or the track to write.

*bSecure*

Specifies whether or not to do a security check.

*lpszTrack1Fields*

Pointer to a list of null-terminated field names of Track 1, with the final name terminating with two null characters.

*lpszTrack2Fields*

Pointer to a list of null-terminated field names of Track 2, with the final name terminating with two null characters.

*lpszTrack3Fields*

Pointer to a list of null-terminated field names of Track 3, with the final name terminating with two null characters.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_FORMNOTFOUND	The specified form cannot be found.
WFS_ERR_IDC_FORMINVALID	The specified form is invalid.

**Comments** None.

## 5. Execute Commands

---

### 5.1 WFS\_CMD\_IDC\_READ\_TRACK

---

**Description** For motor driven card readers, the ID card unit checks whether a card has been inserted. If so, the tracks are read immediately as described in the form specified by the *lpstrFormsName* parameter.

If no card has been inserted, and for all other categories of card readers, the ID card unit waits for the period of time specified in the **WFSExecute** call for a card to be either inserted or pulled through. Again the next step is reading the tracks specified in the form (see Section 7, Form Definition, for a more detailed description of the forms mechanism). In addition to that, the results of a security check via a security module (i.e., MM, CIM86) are specified and added to the track data.

If the security check fails however this should not stop valid data being returned. In this situation the error WFS\_ERR\_IDC\_SECURITYFAIL will be returned if the form specifies only security data to be read, in all other cases WFS\_SUCCESS will be returned with the security field of the output parameter set to WFS\_IDC\_SEC\_HWERROR.

**Input Param** LPSTR lpstrFormName;

*lpstrFormName*

Points to the name of the form that defines the behaviour for the reading of tracks (see Section 6, Form Definition).

**Output Param** LPSTR lpstrTrackData;

*lpstrTrackData*

Points to the data read successfully from the selected tracks (and value of security module if available).

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error. Operator intervention is required.
WFS_ERR_IDC_INVALIDDATA	The read operation specified by the forms definition could not be completed successfully due to invalid track data. This is returned if all tracks in an 'or' ( ) operation cannot be read or if any track in an 'and' (&) operation cannot be read. <i>lpstrTrackData</i> points to data from the successfully read tracks (if any). One execute event (WFS_EXEE_IDC_INVALIDTRACKDATA) is generated for each specified track which could not be read successfully. See the form description for the rules defining how tracks are specified.
WFS_ERR_IDC_NOMEDIA	The card was removed before completion of the read action (the event WFS_EXEE_IDC_MEDIAINserted has been generated). For motor driven devices, the read is disabled; i.e another command has to be issued to enable the reader for card entry.
WFS_ERR_IDC_INVALIDMEDIA	No track found; card may have been inserted or pulled through the wrong way.
WFS_ERR_IDC_FORMNOTFOUND	The specified form can not be found.
WFS_ERR_IDC_FORMINVALID	The specified form definition is invalid (e.g., syntax error).
WFS_ERR_IDC_SECURITYFAIL	The security module failed reading the cards security sign.
WFS_ERR_IDC_CARDTOOSHORT	The card that was inserted is too short. When this error occurs the card remains at the exit slot.

## CWA 14050-4:2003 (E)

WFS\_ERR\_IDC\_CARDTOOLONG The card that was inserted is too long. When this error occurs the card remains at the exit slot.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command

Value	Meaning
WFS_EXEE_IDC_INVALIDTRACKDATA	One event is generated for each blank track (no data) or invalid track (either data error reading the track or the data does not conform to the specified form definition).
WFS_EXEE_IDC_MEDIINSERTED	This event is generated when a card is detected in the device, giving early warning of card entry to an application, allowing it to remove a user prompt and/or do other processing while the card is being read.
WFS_SRVE_IDC_MEDIAREMOVED	This event is generated when a card is removed before completion of a read operation.
WFS_EXEE_IDC_INVALIDMEDIA	The user is attempting to insert the media in the wrong orientation. The card has not been accepted into the device. The device is still ready to accept a card inserted in the correct orientation.

**Comments** The track data is preceded by the keyword for the track, separated by a ':'. The field data is always preceded by the corresponding keyword, separated by a '='. The fields are separated by 0x00. The data of the different tracks is separated by an additional 0x00. The end of the buffer is marked by another additional 0x00 (see example below). Data encoding is defined in Section 6, Form Definition.

Example of *lpstrTrackData*:

```
TRACK2:ALL=47.. \0\0TRACK3:MI=59\0PAN=500.. \0\0\0
```

## 5.2 WFS\_CMD\_IDC\_WRITE\_TRACK

**Description** For motor-driven card readers, the ID card unit checks whether a card has been inserted. If so, the data is written to the track as described in the form specified by the *lpstrFormName* parameter, and the other parameters.

If no card has been inserted, and for all other categories of devices, the ID card unit waits for the period of time specified in the **WFSExecute** call for a card to be either inserted or pulled through. The next step is writing the data defined by the form and the parameters to the respective track (see Section 7, Form Definition, for a more detailed description of the forms mechanism).

This procedure is followed by data verification.

If power fails during a write the outcome of the operation will be vendor specific, there is no guarantee that the write will have succeeded.

**Input Param** LPWFSIDCWITETRACK lpWriteTrack;

```
struct _wfs_idc_write_track
{
    LPSTR          lpstrFormName;
    LPSTR          lpstrTrackData;
    WORD           fwWriteMethod;
} WFSIDCWITETRACK, * LPWFSIDCWITETRACK;
```

*lpstrFormName*

Points to the name of the form to be used.

*lpstrTrackData*

Points to the data to be used in the form.



*fwWriteMethod*

Indicates whether a low coercivity or high coercivity magnetic stripe is being written.

Value	Meaning
WFS_IDC_LOCO	Low coercivity magnetic stripe is being written.
WFS_IDC_HICO	High coercivity magnetic stripe is being written.
WFS_IDC_AUTO	Service provider will determine whether low or high coercivity stripe is to be written.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error. Operator intervention is required
WFS_ERR_IDC_NOMEDIA	The card was removed before completion of the write action (the event WFS_EXEE_IDC_MEDIINSERTED has been generated). For motor driven devices, the write is disabled; i.e. another command has to be issued to enable the reader for card entry.
WFS_ERR_IDC_INVALIDDATA	An error occurred while writing the track.
WFS_ERR_IDC_DATASYNTAX	The syntax of the data pointed to by <i>lpstrTrackData</i> is in error, or does not conform to the form definition.
WFS_ERR_IDC_INVALIDMEDIA	No track found; card may have been inserted or pulled through the wrong way.
WFS_ERR_IDC_FORMNOTFOUND	The specified form can not be found.
WFS_ERR_IDC_FORMINVALID	The specified form definition is invalid (e.g., syntax error).
WFS_ERR_IDC_WRITE_METHOD	The <i>fwWriteMethod</i> value is inconsistent with device capabilities.
WFS_ERR_IDC_CARDTOOSHORT	The card that was inserted is too short. When this error occurs the card remains at the exit slot.
WFS_ERR_IDC_CARDTOOLONG	The card that was inserted is too long. When this error occurs the card remains at the exit slot.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command:

Value	Meaning
WFS_EXEE_IDC_INVALIDTRACKDATA	One event is generated for each blank track (no data) or invalid track (either data error reading the track or the data does not conform to the specified form definition).
WFS_EXEE_IDC_MEDIINSERTED	This event is generated when a card is detected in the device, giving early warning of card entry to an application, allowing it to remove a user prompt and/or do other processing while the card is being written.
WFS_SRVE_IDC_MEDIAREMOVED	This event is generated when a card is removed before completion of a write operation.
WFS_EXEE_IDC_INVALIDMEDIA	The user is attempting to insert the media in the wrong orientation. The card has not been accepted into the device. The device is still ready to accept a card inserted in the correct orientation.

**Comments** The field data is always preceded by the corresponding keyword, separated by an '='. This keyword could be one of the fields defined in the form or the predefined keyword 'ALL'. Fields are separated by 0x00. The end of the buffer is marked with an additional 0x00. (See the example below and Section 6, Form Definition.). This specification means that only one track can be

## CWA 14050-4:2003 (E)

written in the same command. This is a fundamental capability of an ID card unit; thus if a write request is received by a device with no write capability, the WFS\_ERR\_UNSUPP\_COMMAND error is returned.

Example of *lpstrTrackData*:  
RETRYCOUNT=3\0DATE=3132\0\0

### 5.3 WFS\_CMD\_IDC\_EJECT\_CARD

---

**Description** This command is only applicable to motor driven card readers and latched DIP card readers. For motorized card readers, the card is driven to the exit slot from where the user can remove it. The card remains in position for withdrawal until either it is taken or another command is issued that moves the card.

For Latched DIP readers, this command causes the card to be unlatched (if not already unlatched), enabling removal.

. After successful completion of this command, a WFS\_SRVE\_IDC\_MEDIAREMOVED event is generated to inform the application when the card is taken.

**Input Param** None.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error. Operator intervention is required.
WFS_ERR_IDC_NOMEDIA	No card is present.
WFS_ERR_IDC_MEDIARETAINED	The card has been retained during attempts to eject it. The device is clear and can be used.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command:

Value	Meaning
WFS_SRVE_IDC_MEDIAREMOVED	The card has been taken by the user.

**Comments** This is a fundamental capability of an ID card unit; thus if an eject request is received by a device with no eject capability, the WFS\_ERR\_UNSUPP\_COMMAND error is returned.

### 5.4 WFS\_CMD\_IDC\_RETAIN\_CARD

---

**Description** The card is removed from its present position (card inserted into device, card entering, unknown position) and stored in the retain bin; applicable to motor-driven card readers only. The ID card unit sends an event, if the storage capacity of the retain bin is reached. If the storage capacity has already been reached, and the command cannot be executed, an error is returned and the card remains in its present position.

**Input Param** None.

**Output Param** LPWFSIDCRETAINCARD lpRetainCard;

```
typedef struct _wfs_idc_retain_card
{
    USHORT    usCount;
    WORD     fwPosition;
} WFSIDCRETAINCARD, * LPWFSIDCRETAINCARD;
```

*usCount*

Total number of ID cards retained up to and including this operation, since the last WFS\_CMD\_IDC\_RESET\_COUNT command was executed.

*fwPosition*

Position of card; only relevant if card could not be retained. Possible positions:

Value	Meaning
WFS_IDC_MEDIAUNKNOWN	The position of the card can not be determined with the device in its current state.
WFS_IDC_MEDIAPRESENT	The card is present in the reader.
WFS_IDC_MEDIAENTERING	The card is in the entering position (shutter).

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_NOMEDIA	No card has been inserted. The <i>fwPosition</i> parameter has the value WFS_IDC_MEDIAUNKNOWN.
WFS_ERR_IDC_RETAINBINFULL	The retain bin is full; no more cards can be retained. The current card is still in the device.
WFS_ERR_IDC_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error. Operator intervention is required.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command:

Value	Meaning
WFS_USRE_IDC_RETAINBINTHRESHOLD	The retain bin reached a threshold value.
WFS_SRVE_IDC_MEDIAREMOVED	The card has been taken by the user.
WFS_EXEE_IDC_MEDIARETAINED	The card has been retained.

**Comments** This is a fundamental capability of an ID card unit; thus if a retain request is received by a device with no retain capability, the WFS\_ERR\_UNSUPP\_COMMAND error is returned.

## 5.5 WFS\_CMD\_IDC\_RESET\_COUNT

**Description** This function resets the present value for number of cards retained to zero. The function is possible for motor-driven card readers only.

The number of cards retained is controlled by the service and can be requested before resetting via the WFS\_INF\_IDC\_STATUS.

**Input Param** None.

**Output Param** None.

**Error Codes** Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command:

Value	Meaning
WFS_USRE_IDC_RETAINBINTHRESHOLD	The retain bin was emptied.

**Comments** This is a fundamental capability of an ID card unit; thus if this request is received by a device with no retain capability, the WFS\_ERR\_UNSUPP\_COMMAND error is returned.

## 5.6 WFS\_CMD\_IDC\_SETKEY

**Description** This command is used for setting the DES key that is necessary for operating a CIM86 module. The command must be executed before the first read command is issued to the card reader.

**Input Param** LPWFSIDCSETKEY lpSetkey;

```
typedef struct _wfs_idc_setkey
{
    USHORT    usKeyLen;
    LPBYTE    lpbKeyValue;
} WFSIDCSETKEY, *LPWFSIDCSETKEY;
```

*usKeyLen*  
Specifies the length of the following key value.

## CWA 14050-4:2003 (E)

### *lpbKeyValue*

Pointer to a byte array containing the CIM86 DES key. This key is supplied by the vendor of the CIM86 module.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_INVALIDKEY	The key does not fit to the security module.

**Events** Only the generic events defined in [Ref. 1] can be generated by this command.

**Comments** None.

## 5.7 WFS\_CMD\_IDC\_READ\_RAW\_DATA

**Description** For motor driven card readers, the ID card unit checks whether a card has been inserted. If so, all specified tracks are read immediately. If reading the chip is requested, the chip will be contacted and reset and the ATR (Answer To Reset) data will be read. When this command completes the chip will be in contacted position. This command can also be used for an explicit cold reset of a previously contacted chip.

This command should only be used for user cards and should not be used for permanently connected chips.

If no card has been inserted, and for all other categories of card readers, the ID card unit waits for the period of time specified in the **WFSExecute** call for a card to be either inserted or pulled through. The next step is trying to read all tracks specified.

Magnetic stripe track data is converted from its 5 or 7 bit character form to 8 bit ASCII form. The parity bit from each 5 or 7 bit magnetic stripe character is discarded. Start and end sentinel characters are not returned to the application. Field separator characters are returned to the application, and are also converted to 8 bit ASCII form.

In addition to that, a security check via a security module (i.e., MM, CIM86) can be requested. If the security check fails however this should not stop valid data being returned. In this situation the error WFS\_ERR\_IDC\_SECURITYFAIL will be returned if the command specifies only security data to be read, in all other cases WFS\_SUCCESS will be returned with the lpbData field of the output parameter set to WFS\_IDC\_SEC\_HWERROR.

If the card unit is a latched DIP unit then the device will latch the card when the chip card will be read, i.e. WFS\_IDC\_CHIP is specified (see below). The card will remain latched until a call to WFS\_CMD\_IDC\_EJECT\_CARD is made.

**Input Param** LPWORD lpwReadData;

### *lpwReadData*

Specifies the data that should be read as a combination of the following flags:

Value	Meaning
WFS_IDC_TRACK1	Track 1 of the magnetic stripe will be read.
WFS_IDC_TRACK2	Track 2 of the magnetic stripe will be read.
WFS_IDC_TRACK3	Track 3 of the magnetic stripe will be read.
WFS_IDC_CHIP	The chip will be read.
WFS_IDC_SECURITY	A security check will be performed.
WFS_IDC_FLUXINACTIVE	If the IDC Flux Sensor is programmable it will be disabled in order to allow chip data to be read on cards which have no magnetic stripes.
WFS_IDC_TRACK_WM	The Swedish Watermark track will be read.

**Output Param** LPWFSIDCCARDDATA \*lppCardData;

### *lppCardData*

Pointer to a null-terminated array of pointers to card data structures:

```

struct _wfs_idc_card_data
{
    WORD            wDataSource;
    WORD            wStatus;
    ULONG           ulDataLength;
    LPBYTE          lpbData;
    WORD            fwWriteMethod;
} WFSIDCCARDDATA, * LPWFSIDCCARDDATA;

```

*wDataSource*

Specifies the source of the card data as one of the following flags:

Value	Meaning
WFS_IDC_TRACK1	<i>lpbData</i> contains data read from track 1.
WFS_IDC_TRACK2	<i>lpbData</i> contains data read from track 2.
WFS_IDC_TRACK3	<i>lpbData</i> contains data read from track 3.
WFS_IDC_CHIP	<i>lpbData</i> contains ATR data read from the chip.
WFS_IDC_SECURITY	<i>lpbData</i> contains the value returned by the security module.
WFS_IDC_TRACK_WM	<i>lpbData</i> contains data read from the Swedish Watermark track.

*wStatus*

Status of reading the card data. Possible values are:

Value	Meaning
WFS_IDC_DATAOK	The data is ok.
WFS_IDC_DATAMISSING	The track/chip is blank.
WFS_IDC_DATAINVALID	The data contained on the track/chip is invalid.
WFS_IDC_DATATOOLONG	The data contained on the track/chip is too long.
WFS_IDC_DATATOOSHORT	The data contained on the track/chip is too short.
WFS_IDC_DATASRCNOTSUPP	The data source to read from is not supported by the service provider.
WFS_IDC_DATASRCMISSING	The data source to read from is missing on the card.

*ulDataLength*

Specifies the length of the following field *lpbData*.

*lpbData*

Points to the data read from the track/chip or the value returned by the security module. The security module can return one of the following values:

Value	Meaning
WFS_IDC_SEC_READLEVEL1	The security data readability level is 1.
WFS_IDC_SEC_READLEVEL2	The security data readability level is 2.
WFS_IDC_SEC_READLEVEL3	The security data readability level is 3.
WFS_IDC_SEC_READLEVEL4	The security data readability level is 4.
WFS_IDC_SEC_READLEVEL5	The security data readability level is 5.
WFS_IDC_SEC_BADREADLEVEL	The security data reading quality is not acceptable.
WFS_IDC_SEC_NODATA	There are no security data on the card.
WFS_IDC_SEC_DATAINVAL	The validation of the security data with the specific data on the magnetic stripe was not successful.
WFS_IDC_SEC_HWERROR	The security module could not be used, because of a hardware error.
WFS_IDC_SEC_NOINIT	The security module could not be used, because it was not initialized (e.g. CIM key is not loaded).

*fwWriteMethod*

Ignored for this command.

**Error Codes**

In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error. Operator intervention is required.
WFS_ERR_IDC_NOMEDIA	The card was removed before completion of the read action (the event WFS_EXEE_IDC_MEDIAINserted has been

## CWA 14050-4:2003 (E)

	generated). For motor driven devices, the read is disabled; i.e. another command has to be issued to enable the reader for card entry.
WFS_ERR_IDC_INVALIDMEDIA	No track or chip found; card may have been inserted or pulled through the wrong way.
WFS_ERR_IDC_CARDTOOSHORT	The card that was inserted is too short. When this error occurs the card remains at the exit slot.
WFS_ERR_IDC_CARDTOOLONG	The card that was inserted is too long. When this error occurs the card remains at the exit slot.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
WFS_EXEE_IDC_MEDIAINsertED	This event is generated when a card is detected in the device, giving early warning of card entry to an application, allowing it to remove a user prompt and/or do other processing while the card is being read.
WFS_SRVE_IDC_MEDIAREMOVED	This event is generated when a card is removed before completion of a read operation.
WFS_EXEE_IDC_INVALIDMEDIA	The user is attempting to insert the media in the wrong orientation. The card has not been accepted into the device. The device is still ready to accept a card inserted in the correct orientation.

**Comments** None.

## 5.8 WFS\_CMD\_IDC\_WRITE\_RAW\_DATA

**Description** For motor-driven card readers, the ID card unit checks whether a card has been inserted. If so, the data is written to the tracks.

If no card has been inserted, and for all other categories of devices, the ID card unit waits for the period of time specified in the **WFSExecute** call for a card to be either inserted or pulled through. The next step is writing the data to the respective tracks.

The application must pass the magnetic stripe data in ASCII without any sentinels. The data will be converted by the service provider (ref **WFS\_CMD\_IDC\_READ\_RAW\_DATA**). If the data passed in is too long the **WFS\_ERR\_INVALID\_DATA** error code will be returned.

This procedure is followed by data verification.

If power fails during a write the outcome of the operation will be vendor specific, there is no guarantee that the write will have succeeded.

**Input Param** LPWFSIDCCARDDATA \*lppCardData;

Pointer to a null-terminated array of pointers to card data structures:

```
struct _wfs_idc_card_data
{
    WORD          wDataSource;
    WORD          wStatus;
    ULONG         ulDataLength;
    LPBYTE        lpbData;
    WORD          fwWriteMethod;
} WFSIDCCARDDATA, * LPWFSIDCCARDDATA;
```

*wDataSource*

Specifies the source of the card data as one of the following flags:

Value	Meaning
WFS_IDC_TRACK1	<i>lpbData</i> contains data to be written to track 1.
WFS_IDC_TRACK2	<i>lpbData</i> contains data to be written to track 2.
WFS_IDC_TRACK3	<i>lpbData</i> contains data to be written to track 3.

*wStatus*

This parameter is ignored by this command.

*ulDataLength*

Specifies the length of the following field *lpbData*.

*lpbData*

Points to the data to be written to the track.

*fwWriteMethod*

Indicates whether a loco or hico magnetic stripe is being written.

Value	Meaning
WFS_IDC_LOCO	Low coercivity magnetic stripe is being written.
WFS_IDC_HICO	High coercivity magnetic stripe is being written.
WFS_IDC_AUTO	Service provider will determine whether low or high coercivity stripe is to be written.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error. Operator intervention is required
WFS_ERR_IDC_NOMEDIA	The card was removed before completion of the write action (the event WFS_EXEE_IDC_MEDIAINsertED has been generated). For motor driven devices, the write is disabled; i.e. another command has to be issued to enable the reader for card entry.
WFS_ERR_IDC_INVALIDMEDIA	No track found; card may have been inserted or pulled through the wrong way.
WFS_ERR_IDC_WRITE_METHOD	The fwWriteMethod value is inconsistent with device capabilities.
WFS_ERR_IDC_CARDTOOSHORT	The card that was inserted is too short. When this error occurs the card remains at the exit slot.
WFS_ERR_IDC_CARDTOOLONG	The card that was inserted is too long. When this error occurs the card remains at the exit slot.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
WFS_EXEE_IDC_MEDIAINsertED	This event is generated when a card is detected in the device, giving early warning of card entry to an application, allowing it to remove a user prompt and/or do other processing while the card is being written.
WFS_SRVE_IDC_MEDIAREMOVED	This event is generated when a card is removed before completion of a write operation.
WFS_EXEE_IDC_INVALIDMEDIA	The user is attempting to insert the media in the wrong orientation. The card has not been accepted into the device. The device is still ready to accept a card inserted in the correct orientation.

**Comments** This is a fundamental capability of an ID card unit; thus if a write request is received by a device with no write capability, the WFS\_ERR\_UNSUPP\_COMMAND error is returned.

## 5.9 WFS\_CMD\_IDC\_CHIP\_IO

**Description** This command is used to communicate with the chip. Transparent data is sent from the application to the chip and the response of the chip is returned transparently to the application.

The ATR of the chip must be obtained before issuing this command. The ATR for a user card must initially be obtained through WFS\_CMD\_IDC\_READ\_RAW\_DATA. The ATR for subsequent resets of a user card can be obtained either through WFS\_CMD\_IDC\_READ\_RAW\_DATA command or through WFS\_CMD\_IDC\_CHIP\_POWER. The ATR for permanent connected chips is always obtained through WFS\_CMD\_IDC\_CHIP\_POWER.

**Input Param** LPWFSIDCCHIPIO lpChipIoIn;  
 struct \_wfs\_idc\_chip\_io  
 {  
   WORD wChipProtocol;  
   ULONG ulChipDataLength;  
   LPBYTE lpbChipData;  
 } WFSIDCCHIPIO, \* LPWFSIDCCHIPIO;

*wChipProtocol*

Identifies the protocol that is used to communicate with the chip. Possible values are those described in WFS\_INF\_IDC\_CAPABILITIES.

*ulChipDataLength*

Specifies the length of the following field *lpbChipData*.

*lpbChipData*

Points to the data sent to the chip.

**Output Param** LPWFSIDCCHIPIO lpChipIoOut;  
 struct \_wfs\_idc\_chip\_io  
 {  
   WORD wChipProtocol;  
   ULONG ulChipDataLength;  
   LPBYTE lpbChipData;  
 } WFSIDCCHIPIO, \* LPWFSIDCCHIPIO;

*wChipProtocol*

Identifies the protocol that is used to communicate with the chip. This field contains the same value as the corresponding field in the input structure.

*ulChipDataLength*

Specifies the length of the following field *lpbChipData*.

*lpbChipData*

Points to the data responded from the chip.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_NOMEDIA	There is no card inside the device.
WFS_ERR_IDC_INVALIDMEDIA	No chip found; card may have been inserted the wrong way.
WFS_ERR_IDC_INVALIDDATA	An error occurred while communicating with the chip.
WFS_ERR_IDC_PROTOCOLNOTSUPP	The protocol used was not supported by the service provider.
WFS_ERR_IDC_ATRNOTOBTAINED	The ATR was not obtained before by issuing a Read Command.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
WFS_SRVE_IDC_MEDIAREMOVED	This event is generated when a card is removed before completion of an operation.



**Comments** None.

## 5.10 WFS\_CMD\_IDC\_RESET

---

**Description** This command is used by the application to perform a hardware reset which will attempt to return the IDC device to a known good state. This command does not over-ride a lock obtained by another application or service handle.

If the device is a user ID card unit, the device will attempt to either retain, eject or will perform no action on any user cards found in the IDC as specified in the `lpwResetIn` parameter. It may not always be possible to retain or eject the items as specified because of hardware problems. If a user card is found inside the device the `WFS_SRVE_IDC_MEDIADETECTED` event will inform the application where card was actually moved to. If no action is specified the user card will not be moved even if this means that the IDC cannot be recovered.

If the device is a permanent chip card unit, this command will power-off the chip.

**Input Param** LPWORD `lpwResetIn`;

Specifies the action to be performed on any user card found within the ID card unit as one of the following values:

Value	Meaning
<code>WFS_IDC_EJECT</code>	Eject any card found.
<code>WFS_IDC_RETAIN</code>	Retain any card found.
<code>WFS_IDC_NOACTION</code>	No action should be performed on any card found.

If this value is NULL. The service provider will determine where to move any card found.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
<code>WFS_ERR_IDC_MEDIAJAM</code>	The card is jammed. Operator intervention is required.
<code>WFS_ERR_IDC_SHUTTERFAIL</code>	The device is unable to open and close it's shutter

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
<code>WFS_SRVE_IDC_MEDIADETECTED</code>	This event is generated when a media is detected during a reset.

**Comments** None

## 5.11 WFS\_CMD\_IDC\_CHIP\_POWER

---

**Description** This command handles the power actions that can be done on the chip. This command is only used for user chips after the chip has been contacted for the first time using the `WFS_CMD_IDC_READ_RAW_DATA` command. This command is the only way to control the chip power for permanently connected chip cards.

**Input Param** LPWORD `lpwChipPower`;

*lpwChipPower*

Specifies the action to perform as one of the following flags:

Value	Meaning
<code>WFS_IDC_CHIPPOWERCOLD</code>	The chip is powered on and reset (Cold Reset).
<code>WFS_IDC_CHIPPOWERWARM</code>	The chip is reset (Warm Reset).
<code>WFS_IDC_CHIPPOWEROFF</code>	The chip is powered off.

**Output Param** NULL or LPWFSIDCCHIPPOWEROUT `lpChipPowerOut`;

## CWA 14050-4:2003 (E)

```
struct _wfs_idc_chip_power_out
{
    ULONG          ulChipDataLength;
    LPBYTE         lpbChipData;
} WFSIDCCHIPPOWEROUT, * LPWFSIDCCHIPPOWEROUT;
```

### *ulChipDataLength*

Specifies the length of the following field *lpbChipData*.

### *lpbChipData*

Points to the ATR data responded from the chip. NULL if the action was not a power on.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_IDC_CHIPPOWERNOTSUPP	The specified action is not supported by the hardware device.
WFS_ERR_IDC_MEDIAJAM	The card is jammed. Operator intervention is required.
WFS_ERR_IDC_NOMEDIA	There is no card inside the device.
WFS_ERR_IDC_INVALIDMEDIA	No chip found; card may have been inserted or pulled through the wrong way.
WFS_ERR_IDC_INVALIDDATA	An error occurred while communicating with the chip.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
WFS_SRVE_IDC_MEDIAREMOVED	This event is generated when a card is removed before completion of the operation.

**Comments** The NULL return value for the output parameter is provided for backwards compatibility and is only valid for user cards. Permanent chips must return the ATR in the output parameter. User cards should return the ATR in the output parameter.

## 5.12 WFS\_CMD\_IDC\_PARSE\_DATA

**Description** This command takes form name and the output of a successful WFS\_CMD\_IDC\_READ\_RAW\_DATA command and returns the parsed string.

**Input Param** LPWFSIDCPARSEDATA lpParseData;

```
typedef struct _wfs_idc_parse_data
{
    LPSTR          lpstrFormName;
    LPWFSIDCCARDDATA *lppCardData;
} WFSIDCPARSEDATA, * LPWFSIDCPARSEDATA;
```

### *lpstrFormName*

Points to the name of the form that defines the behaviour for the reading of tracks (see Section 6, Form Description).

### *lppCardData*

Points to a null-terminated array of pointers to card data structures, as returned from the WFS\_CMD\_IDC\_READ\_RAW\_DATA command.

**Output Param** LPSTR lpstrTrackData;

### *lpstrTrackData*

Points to the data read successfully from the selected tracks (and value of security module if available).

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
-------	---------

WFS_ERR_IDC_INVALIDDATA	The read operation specified by the forms definition could not be completed successfully due to invalid or incomplete track data being passed in. This is returned if none of the tracks in an 'or' ( ) operation is contained in the <i>lppCardData</i> array or if any track in an 'and' (&) operation is not found in the input. One execute event (WFS_EXEE_IDC_INVALIDTRACKDATA) is generated for each specified track which could not be parsed successfully. See the form description for the rules defining how tracks are specified.
WFS_ERR_IDC_FORMNOTFOUND	The specified form can not be found.
WFS_ERR_IDC_FORMINVALID	The specified form definition is invalid (e.g., syntax error).

**Events**

In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
WFS_EXEE_IDC_INVALIDTRACKDATA	One event is generated for each blank track (no data) or invalid track (either data error reading the track or the data does not conform to the specified form definition).

**Comments**

The track data is preceded by the keyword for the track, separated by a ':'. The field data is always preceded by the corresponding keyword, separated by a '='. The fields are separated by 0x00. The data of the different tracks is separated by an additional 0x00. The end of the buffer is marked by another additional 0x00 (see example below). Data encoding is defined in Section 6, Form Definition.

Example of *lpstrTrackData*:

```
TRACK2:ALL=47.. \0\0TRACK3:MI I=59\0PAN=500.. \0\0\0
```

## 6. Events

---

### 6.1 WFS\_EXEE\_IDC\_INVALIDTRACKDATA

---

**Description** This execute event specifies that a track contained invalid or no data.

**Event Param** LPWFSIDCTRACKEVENT lpTrackEvent;

```

struct _wfs_idc_track_event
{
    WORD          fwStatus;
    LPSTR         lpstrTrack;
    LPSTR         lpstrData;
} WFSIDCTRACKEVENT, * LPWFSIDCTRACKEVENT;

```

*fwStatus*

Status of reading the track. Possible values are:

Value	Meaning
WFS_IDC_DATAMISSING	The track is blank.
WFS_IDC_DATAINVALID	The data contained on the track is invalid.
WFS_IDC_DATATOOLONG	The data contained on the track is too long.
WFS_IDC_DATATOOSHORT	The data contained on the track is too short.

*lpstrTrack*

Points to the keyword of the track on which the error occurred.

*lpstrData*

Points to the data that could be read (that may be only a fragment of the track), terminated by a null character. This data is simply a stream of characters; it does not contain keywords.

### 6.2 WFS\_EXEE\_IDC\_MEDIINSERTED

---

**Description** This execute event specifies that a card was inserted into the device.

**Event Param** None.

### 6.3 WFS\_SRVE\_IDC\_MEDIAREMOVED

---

**Description** This service event specifies that the inserted card was manually removed by the user during the processing of a read/write command, after an eject operation, or after the card is removed by the user in a latched DIP card unit.

**Event Param** None.

### 6.4 WFS\_EXEE\_IDC\_MEDIARETAINED

---

**Description** This service event specifies that the card was retained.

**Event Param** None.

### 6.5 WFS\_EXEE\_IDC\_INVALIDMEDIA

---

**Description** This execute event specifies that the media the user is attempting to insert is not a valid card or it is a card but it is in the wrong orientation.

**Event Param** None.

## 6.6 WFS\_SRVE\_IDC\_CARDACTION

---

**Description** This service event specifies that a card has been retained or ejected by either the automatic power on or power off action of the device.

**Event Param** LPWFSIDCCARDACT lpCardAct;

```
typedef struct _wfs_idc_card_act
{
    WORD          wAction;
    WORD          wPosition;
} WFSIDCCARDACT, * LPWFSIDCCARDACT;
```

*wAction*

Specifies which action has been performed with the card. Possible values are:

Value	Meaning
WFS_IDC_CARDRETAINED	The card has been retained.
WFS_IDC_CARDEJECTED	The card has been ejected.
WFS_IDC_CARDREADPOSITION	The card has been moved to the read position

*wPosition*

Position of card before being retained or ejected. Possible values are:

Value	Meaning
WFS_IDC_MEDIAUNKNOWN	The position of the card can not be determined.
WFS_IDC_MEDIAPRESENT	The card was present in the reader.
WFS_IDC_MEDIAENTERING	The card was entering the reader.

## 6.7 WFS\_USRE\_IDC\_RETAINBINTHRESHOLD

---

**Description** This user event specifies that the retain bin holding the retained cards has reached a threshold condition or the threshold condition is removed.

**Event Param** LPWORD lpfwRetainBin;

*lpfwRetainBin*

Specifies the state of the ID card unit retain bin as one of the following values:

Value	Meaning
WFS_IDC_RETAINBINOK	The retain bin of the ID card unit was emptied.
WFS_IDC_RETAINBINFULL	The retain bin of the ID card unit is full.
WFS_IDC_RETAINBINHIGH	The retain bin of the ID card unit is nearly full.

## 6.8 WFS\_SRVE\_IDC\_MEDIADETECTED

---

**Description** This service event is generated if media is detected during a reset (WFS\_CMD\_IDC\_RESET). The parameter on the event informs the application of the position of the card on the completion of the reset.

**Event Param** LPWORD \* lpwResetOut;

Specifies the action that was performed on any card found within the IDC as one of the following values:

Value	Meaning
WFS_IDC_CARDEJECTED	The card was ejected.
WFS_IDC_CARDRETAINED	The card was retained.
WFS_IDC_CARDREADPOSITION	The card is in read position.
WFS_IDC_CARDJAMMED	The card is jammed in the device.

## 7. Form Description

---

This section describes the forms mechanism used to define the tracks to be read or written. Forms are contained in a single file, with one section for each defined form. The name of each section is the form name parameter in the WFS\_CMD\_IDC\_READ\_TRACK and WFS\_CMD\_IDC\_WRITE\_TRACK commands.

The way to specify the location of a form file is vendor dependent.

As an example the following registry information can be used:

```
WOSA/XFS_ROOT
  FORMS
    IDCU
      formfile=<path><filename>
```

The read form defines which tracks should be read in the WFS\_CMD\_IDC\_READ\_TRACK command and what the response should be to a read failure. The read form can also be used to define logical track data, i.e. fields like "account number," "issuer identifier," and their position within the physical track data. For example, the output parameter of the WFS\_CMD\_IDC\_READ\_TRACK command with input parameter *lpstrFormName* = READTRACK3GERMAN could look like (see example 1 below):

```
"TRACK3:MII=59\0COUNTRY=280\0ISSUERID=50050500\0ACCOUNT=1234567890\0LUHNT3=1\0
  EXPIRATION=9912\0SECURE=1\0\0"
```

The write form defines which track is to be written, the logical track data that is handed over in the WFS\_CMD\_IDC\_WRITE\_TRACK command, and how the write data is to be converted to the physical data to be written.

Reserved Keywords/Operands <sup>1</sup>	Meaning
[]	form name delimiters
TRACK1	keyword to identify track 1
TRACK2	keyword to identify track 2
TRACK3	keyword to identify track 3
FIELDSEPT1	value of field separator of track 1
FIELDSEPT2	value of field separator of track 2
FIELDSEPT3	value of field separator of track 3
READ	description of read action; the TRACKn keywords are processed left to right
WRITE	description of write action
ALL	read or write the complete track
SECURE	do the security check via the security module (CIM86 or MM)
&	read/write all tracks specified, abort reading on read failure
	read/write at least one of the tracks specified, continue reading on read failure
FIELDSEPPOS <sub>n</sub>	position of the <i>n</i> th occurrence of field separator on track. FIELDSEPPOS0 specifies the beginning of the data.
,	separator in a list of logical fields
DEFAULT	string for default substitution of track data to be written, that is not defined explicitly by the form fields. DEFAULT also allows an application to input fewer fields than those defined by the form.
?	Reserved value for DEFAULT keyword: substitute track data to write with its value read before.
ENDTRACK	represents the end of the data. It is used to identify fields positioned after the last field separator

<sup>1</sup> Attributes are not required in any mandatory order.

**Notes**

The & and | operands may be combined in a single READ statement; for example:

- read track3 or track2, trying track3 first:  
READ= TRACK3 | TRACK2
  - read track 3 and at least one of track2 or track1:  
READ= TRACK3 & (TRACK2 | TRACK1)
- or:
- READ= TRACK2 | TRACK1 & TRACK3

The keywords FIELDSEPOS0 and ENDTRACK are used as follows:

- read the first 2 bytes of a track:  
FIRST= FIELDSEPOS0 + 1, FIELDSEPOS0 + 2
- read the last 2 bytes of a track:  
LAST= ENDTRACK - 2, ENDTRACK - 1

Use of field separators in track layouts is to replace optional fields and terminate variable length fields.

Write forms are designed for updating specific fields without altering the position of the field separators.

The application may alter the position of the field separators by rewriting the card tracks (ALL option or DEFAULT option with default track data).

**Example 1**      Reading tracks:

---

```
[READTRACK3GERMAN]
FIELDSEPT3= =          /* field separator of track 3 */
READ= TRACK3          /* only track 3 must be read */
TRACK3= MII, COUNTRY, ISSUERID, ACCOUNT, LUHNT3, EXPIRATION, SECURE
                                     /* read logical
                                     fields as defined
                                     below; also check the
                                     security */

MII= FIELDSEPOS0 + 3, FIELDSEPOS0 + 4
ISSUERID= FIELDSEPOS0 + 5, FIELDSEPOS1 - 1
ACCOUNT= FIELDSEPOS1 + 1, FIELDSEPOS2 - 2
LUHNT3= FIELDSEPOS2 - 1, FIELDSEPOS2 - 1
COUNTRY= FIELDSEPOS2 + 1, FIELDSEPOS2 + 3
EXPIRATION= FIELDSEPOS2 + 36, FIELDSEPOS2 + 39
```

All tracks must be read ('READ'), that is, the read fails if an error occurs on reading any one of the tracks (the '&' operand). The field "major industry identifier" ('MII') is located after the first field separator ('FIELDSEPOS1') and its length is two bytes. The "issuer identifier" field ('ISSUERID') is located after the MII field, with a length of eight bytes. The next field, "account number" ('ACCOUNT') is variable length; it ends before the luhn digit field ('LUHNT3') that is the last digit in front of the second field separator ('FIELDSEPOS2').

**Example 2**      Write a track:

---

```
[WRITETRACK3]
FIELDSEPT3= =
DEFAULT= ?          /* fields not specified in the write form are to be left
                    unchanged, i.e., read and the same data written back to
                    them */

WRITE= TRACK3
TRACK3= RETRYCOUNT, DATE
RETRYCOUNT= FIELDSEPOS2 + 22, FIELDSEPOS2 + 22
DATE= FIELDSEPOS5 + 1, FIELDSEPOS5 + 4
```

Track 3 is to be written. In the example only the retry counter and the date of the last transaction are updated, the other fields are unchanged.

## CWA 14050-4:2003 (E)

A sample of input data to be used with this form is as follows:

```
RETRYCOUNT=3\0DATE=3132\00
```

### Example 3 Write a track:

---

```
[ WRITETRACK3ALL ]  
WRITE= TRACK3  
TRACK3= ALL
```

Track 3 is to be written. By specifying ALL, the data passed in the WFS\_CMD\_IDC\_WRITE\_TRACK command is written to the physical track without formatting.

A sample of input data to be used with this form is as follows:

```
ALL=123456789123\0\0
```



## 8. Relation with PC/SC

---

The PC/SC (Personal Computer / Smart Card) Workgroup was formed in May 1996 in partnership with major PC and smart card companies. The main focus of the workgroup has been to develop specifications that ensure interoperability among smart cards, smart card readers, and computers made by different manufacturers:

*Interoperability Specification for Integrated Circuit Cards (ICC) and Personal Computer Systems*

Version 1.0 of these specifications were released in December 1997. They are available on the Web at:  
<http://www.pcscworkgroup.com>

The related document *PC/SC Integration Guidelines* describes the relation between XFS and PC/SC and provides guidelines to manage PC/SC compliant readers from the XFS subsystem.

In order to make integration of PC/SC compliant smart cards easier, the following principles have been defined to add new chip capabilities to the IDC Device Class Interface:

- A new set of chip capabilities is made of new queries and commands which should be consistent.
- An associated COM-based interface definition reflects these new queries and commands.
- This COM-based interface definition and its associated GUID are published part of this specification, to allow its implementation in PC/SC ICC service providers.

These principles allow the IDC service provider for a PC/SC compliant reader to be a wrapper for ICC commands, which are handled in the PC/SC subsystem by the corresponding PC/SC ICC service provider.

## 9. C-Header file

---

```

/*****
*
* xfsidc.h      XFS - Identification card unit (IDC) definitions
*
*              Version 3.02 (09/05/03)
*
*****/

#ifndef __INC_XFSIDC__H
#define __INC_XFSIDC__H

#ifdef __cplusplus
extern "C" {
#endif

#include <xfsapi.h>

/* be aware of alignment */
#pragma pack(push,1)

/* values of WFSIDCCAPS.wClass */

#define      WFS_SERVICE_CLASS_IDC                (2)
#define      WFS_SERVICE_CLASS_NAME_IDC          "IDC"
#define      WFS_SERVICE_CLASS_VERSION_IDC       0x0203

#define      IDC_SERVICE_OFFSET                  (WFS_SERVICE_CLASS_IDC * 100)

/* IDC Info Commands */

#define      WFS_INF_IDC_STATUS                   (IDC_SERVICE_OFFSET + 1)
#define      WFS_INF_IDC_CAPABILITIES            (IDC_SERVICE_OFFSET + 2)
#define      WFS_INF_IDC_FORM_LIST              (IDC_SERVICE_OFFSET + 3)
#define      WFS_INF_IDC_QUERY_FORM             (IDC_SERVICE_OFFSET + 4)

/* IDC Execute Commands */

#define      WFS_CMD_IDC_READ_TRACK              (IDC_SERVICE_OFFSET + 1)
#define      WFS_CMD_IDC_WRITE_TRACK            (IDC_SERVICE_OFFSET + 2)
#define      WFS_CMD_IDC_EJECT_CARD             (IDC_SERVICE_OFFSET + 3)
#define      WFS_CMD_IDC_RETAIN_CARD           (IDC_SERVICE_OFFSET + 4)
#define      WFS_CMD_IDC_RESET_COUNT           (IDC_SERVICE_OFFSET + 5)
#define      WFS_CMD_IDC_SETKEY                 (IDC_SERVICE_OFFSET + 6)
#define      WFS_CMD_IDC_READ_RAW_DATA         (IDC_SERVICE_OFFSET + 7)
#define      WFS_CMD_IDC_WRITE_RAW_DATA        (IDC_SERVICE_OFFSET + 8)
#define      WFS_CMD_IDC_CHIP_IO               (IDC_SERVICE_OFFSET + 9)
#define      WFS_CMD_IDC_RESET                 (IDC_SERVICE_OFFSET + 10)
#define      WFS_CMD_IDC_CHIP_POWER           (IDC_SERVICE_OFFSET + 11)
#define      WFS_CMD_IDC_PARSE_DATA            (IDC_SERVICE_OFFSET + 12)

/* IDC Messages */

#define      WFS_EXEE_IDC_INVALIDTRACKDATA      (IDC_SERVICE_OFFSET + 1)
#define      WFS_EXEE_IDC_MEDIAINJECTED         (IDC_SERVICE_OFFSET + 3)
#define      WFS_SRVE_IDC_MEDIAREMOVED         (IDC_SERVICE_OFFSET + 4)
#define      WFS_SRVE_IDC_CARDACTION           (IDC_SERVICE_OFFSET + 5)
#define      WFS_USRE_IDC_RETAINBINTHRESHOLD   (IDC_SERVICE_OFFSET + 6)
#define      WFS_EXEE_IDC_INVALIDMEDIA         (IDC_SERVICE_OFFSET + 7)
#define      WFS_EXEE_IDC_MEDIARETAINED        (IDC_SERVICE_OFFSET + 8)
#define      WFS_SRVE_IDC_MEDIADETECTED        (IDC_SERVICE_OFFSET + 9)

/* values of WFSIDCSTATUS.fwDevice */
#define      WFS_IDC_DEVONLINE                  WFS_STAT_DEVONLINE
#define      WFS_IDC_DEVOFFLINE                 WFS_STAT_DEVOFFLINE
#define      WFS_IDC_DEVPOWEROFF                WFS_STAT_DEVPOWEROFF
#define      WFS_IDC_DEVNODEVICE                WFS_STAT_DEVNODEVICE
#define      WFS_IDC_DEVHWERROR                 WFS_STAT_DEVHWERROR
#define      WFS_IDC_DEVUSERERROR               WFS_STAT_DEVUSERERROR
#define      WFS_IDC_DEVBUSY                    WFS_STAT_DEVBUSY

```

```

/* values of WFSIDCSTATUS.fwMedia, WFSIDCRETAINCARD.fwPosition, */
/* WFSIDCCARDACT.fwPosition */

#define WFS_IDC_MEDIAPRESENT (1)
#define WFS_IDC_MEDIANOTPRESENT (2)
#define WFS_IDC_MEDIAJAMMED (3)
#define WFS_IDC_MEDIANOTSUPP (4)
#define WFS_IDC_MEDIAUNKNOWN (5)
#define WFS_IDC_MEDIAENTERING (6)
#define WFS_IDC_MEDIALATCHED (7)

/* values of WFSIDCSTATUS.fwRetainBin */

#define WFS_IDC_RETAINBINOK (1)
#define WFS_IDC_RETAINNOTSUPP (2)
#define WFS_IDC_RETAINBINFULL (3)
#define WFS_IDC_RETAINBINHIGH (4)

/* values of WFSIDCSTATUS.fwSecurity */

#define WFS_IDC_SECNOTSUPP (1)
#define WFS_IDC_SECNOTREADY (2)
#define WFS_IDC_SECOPEEN (3)

/* values of WFSIDCSTATUS.fwChipPower */

#define WFS_IDC_CHIPONLINE (0)
#define WFS_IDC_CHIPPOWEREDOFF (1)
#define WFS_IDC_CHIPBUSY (2)
#define WFS_IDC_CHIPNODEVICE (3)
#define WFS_IDC_CHIPHWERROR (4)
#define WFS_IDC_CHIPNOCARD (5)
#define WFS_IDC_CHIPNOTSUPP (6)
#define WFS_IDC_CHIPUNKNOWN (7)

/* values of WFSIDCCAPS.fwType */

#define WFS_IDC_TYPEMOTOR (1)
#define WFS_IDC_TYPEWIPE (2)
#define WFS_IDC_TYPEDIP (3)
#define WFS_IDC_TYPECONTACTLESS (4)
#define WFS_IDC_TYPELATCHEDDIP (5)
#define WFS_IDC_TYPEPERMANENT (6)

/* values of WFSIDCCAPS.fwReadTracks, WFSIDCCAPS.fwWriteTracks,
WFSIDCCARDDATA.wDataSource */

#define WFS_IDC_NOTSUPP 0x0000
#define WFS_IDC_TRACK1 0x0001
#define WFS_IDC_TRACK2 0x0002
#define WFS_IDC_TRACK3 0x0004

/* further values of WFSIDCCARDDATA.wDataSource */

#define WFS_IDC_CHIP 0x0008
#define WFS_IDC_SECURITY 0x0010
#define WFS_IDC_FLUXINACTIVE 0x0020
#define WFS_IDC_TRACK_WM 0x8000

/* values of WFSIDCCAPS.fwChipProtocols */

#define WFS_IDC_CHIPT0 0x0001
#define WFS_IDC_CHIPT1 0x0002
#define WFS_IDC_CHIPT2 0x0004
#define WFS_IDC_CHIPT3 0x0008
#define WFS_IDC_CHIPT4 0x0010
#define WFS_IDC_CHIPT5 0x0020
#define WFS_IDC_CHIPT6 0x0040
#define WFS_IDC_CHIPT7 0x0080
#define WFS_IDC_CHIPT8 0x0100
#define WFS_IDC_CHIPT9 0x0200
#define WFS_IDC_CHIPT10 0x0400
#define WFS_IDC_CHIPT11 0x0800
#define WFS_IDC_CHIPT12 0x1000

```

## CWA 14050-4:2003 (E)

```
#define      WFS_IDC_CHIPT13          0x2000
#define      WFS_IDC_CHIPT14          0x4000
#define      WFS_IDC_CHIPT15          0x8000

/* values of WFSIDCCAPS.fwSecType */

#define      WFS_IDC_SECNOTSUPP       (1)
#define      WFS_IDC_SECMBOX          (2)
#define      WFS_IDC_SECCIM86         (3)

/* values of WFSIDCCAPS.fwPowerOnOption, WFSIDCCAPS.fwPowerOffOption, */

#define      WFS_IDC_NOACTION          (1)
#define      WFS_IDC_EJECT             (2)
#define      WFS_IDC_RETAIN            (3)
#define      WFS_IDC_EJECTTHENRETAIN  (4)
#define      WFS_IDC_READPOSITION     (5)

/* values of WFSIDCCAPS.fwWriteMode; WFSIDCWRITETRACK.fwWriteMethod,
WFSIDCCARDDATA.fwWriteMethod */

#define      WFS_IDC_UNKNOWN           0x0001
#define      WFS_IDC_LOCO              0x0002
#define      WFS_IDC_HICO              0x0004
#define      WFS_IDC_AUTO              0x0008

/* values of WFSIDCCAPS.fwChipPower */

#define      WFS_IDC_CHIPPOWERCOLD     0x0002
#define      WFS_IDC_CHIPPOWERWARM    0x0004
#define      WFS_IDC_CHIPPOWEROFF     0x0008

/* values of WFSIDCFORM.fwAction */

#define      WFS_IDC_ACTIONREAD        0x0001
#define      WFS_IDC_ACTIONWRITE      0x0002

/* values of WFSIDCTRACKEVENT.fwStatus, WFSIDCCARDDATA.wStatus */

#define      WFS_IDC_DATAOK            (0)
#define      WFS_IDC_DATAMISSING       (1)
#define      WFS_IDC_DATAINVALID       (2)
#define      WFS_IDC_DATATOOLONG       (3)
#define      WFS_IDC_DATATOOSHORT      (4)
#define      WFS_IDC_DATASRCNOTSUPP    (5)
#define      WFS_IDC_DATASRCMISSING    (6)

/* values WFSIDCCARDDACT.wAction */

#define      WFS_IDC_CARDRETAINED      (1)
#define      WFS_IDC_CARDEJECTED       (2)
#define      WFS_IDC_CARDREADPOSITION  (3)
#define      WFS_IDC_CARDJAMMED        (4)

/* values of WFSIDCCARDDATA.lpbData if security is read */

#define      WFS_IDC_SEC_READLEVEL1    '1'
#define      WFS_IDC_SEC_READLEVEL2    '2'
#define      WFS_IDC_SEC_READLEVEL3    '3'
#define      WFS_IDC_SEC_READLEVEL4    '4'
#define      WFS_IDC_SEC_READLEVEL5    '5'
#define      WFS_IDC_SEC_BADREADLEVEL  '6'
#define      WFS_IDC_SEC_NODATA         '7'
#define      WFS_IDC_SEC_DATAINVAL     '8'
#define      WFS_IDC_SEC_HWERROR        '9'
#define      WFS_IDC_SEC_NOINIT         'A'

/* WOSA/XFS IDC Errors */

#define      WFS_ERR_IDC_MEDIAJAM       (-(IDC_SERVICE_OFFSET + 0))
#define      WFS_ERR_IDC_NOMEDIA        (-(IDC_SERVICE_OFFSET + 1))
#define      WFS_ERR_IDC_MEDIARETAINED  (-(IDC_SERVICE_OFFSET + 2))
#define      WFS_ERR_IDC_RETAINBINFULL  (-(IDC_SERVICE_OFFSET + 3))
#define      WFS_ERR_IDC_INVALIDDATA    (-(IDC_SERVICE_OFFSET + 4))
#define      WFS_ERR_IDC_INVALIDMEDIA   (-(IDC_SERVICE_OFFSET + 5))
```

```

#define WFS_ERR_IDC_FORMNOTFOUND          (-(IDC_SERVICE_OFFSET + 6))
#define WFS_ERR_IDC_FORMINVALID          (-(IDC_SERVICE_OFFSET + 7))
#define WFS_ERR_IDC_DATASYNTAX           (-(IDC_SERVICE_OFFSET + 8))
#define WFS_ERR_IDC_SHUTTERFAIL          (-(IDC_SERVICE_OFFSET + 9))
#define WFS_ERR_IDC_SECURITYFAIL          (-(IDC_SERVICE_OFFSET + 10))
#define WFS_ERR_IDC_PROTOCOLNOTSUPP      (-(IDC_SERVICE_OFFSET + 11))
#define WFS_ERR_IDC_ATRNOTOBTAINED       (-(IDC_SERVICE_OFFSET + 12))
#define WFS_ERR_IDC_INVALIDIDKEY         (-(IDC_SERVICE_OFFSET + 13))
#define WFS_ERR_IDC_WRITE_METHOD         (-(IDC_SERVICE_OFFSET + 14))
#define WFS_ERR_IDC_CHIPPOWERNOTSUPP     (-(IDC_SERVICE_OFFSET + 15))
#define WFS_ERR_IDC_CARDTOOSHORT         (-(IDC_SERVICE_OFFSET + 16))
#define WFS_ERR_IDC_CARDTOOLONG          (-(IDC_SERVICE_OFFSET + 17))

```

```

/*=====*/
/* IDC Info Command Structures and variables */
/*=====*/

```

```

typedef struct _wfs_idc_status
{
    WORD        fwDevice;
    WORD        fwMedia;
    WORD        fwRetainBin;
    WORD        fwSecurity;
    USHORT      usCards;
    WORD        fwChipPower;
    LPSTR       lpszExtra;
} WFSIDCSTATUS, * LPWFSIDCSTATUS;

```

```

typedef struct _wfs_idc_caps
{
    WORD        wClass;
    WORD        fwType;
    BOOL        bCompound;
    WORD        fwReadTracks;
    WORD        fwWriteTracks;
    WORD        fwChipProtocols;
    USHORT      usCards;
    WORD        fwSecType;
    WORD        fwPowerOnOption;
    WORD        fwPowerOffOption;
    BOOL        bFluxSensorProgrammable;
    BOOL        bReadWriteAccessFollowingEject;
    WORD        fwWriteMode;
    WORD        fwChipPower;
    LPSTR       lpszExtra;
} WFSIDCCAPS, * LPWFSIDCCAPS;

```

```

typedef struct _wfs_idc_form
{
    LPSTR       lpszFormName;
    CHAR        cFieldSeparatorTrack1;
    CHAR        cFieldSeparatorTrack2;
    CHAR        cFieldSeparatorTrack3;
    WORD        fwAction;
    LPSTR       lpszTracks;
    BOOL        bSecure;
    LPSTR       lpszTrack1Fields;
    LPSTR       lpszTrack2Fields;
    LPSTR       lpszTrack3Fields;
} WFSIDCFORM, * LPWFSIDCFORM;

```

```

/*=====*/
/* IDC Execute Command Structures */
/*=====*/

```

```

typedef struct _wfs_idc_write_track
{
    LPSTR       lpstrFormName;
    LPSTR       lpstrTrackData;
    WORD        fwWriteMethod;
} WFSIDCWREDITRACK, * LPWFSIDCWREDITRACK;

```

```

typedef struct _wfs_idc_retain_card

```

## CWA 14050-4:2003 (E)

```
{
    USHORT          usCount;
    WORD            fwPosition;
} WFSIDCRETAINCARD, * LPWFSIDCRETAINCARD;

typedef struct _wfs_idc_setkey
{
    USHORT          usKeyLen;
    LPBYTE          lpbKeyValue;
} WFSIDCSETKEY, * LPWFSIDCSETKEY;

typedef struct _wfs_idc_card_data
{
    WORD            wDataSource;
    WORD            wStatus;
    ULONG          ulDataLength;
    LPBYTE          lpbData;
    WORD            fwWriteMethod;
} WFSIDCCARDDATA, * LPWFSIDCCARDDATA;

typedef struct _wfs_idc_chip_io
{
    WORD            wChipProtocol;
    ULONG          ulChipDataLength;
    LPBYTE          lpbChipData;
} WFSIDCCHIPIO, * LPWFSIDCCHIPIO;

typedef struct _wfs_idc_chip_power_out
{
    ULONG          ulChipDataLength;
    LPBYTE          lpbChipData;
} WFSIDCCHIPPOWEROUT, * LPWFSIDCCHIPPOWEROUT;

typedef struct _wfs_idc_parse_data
{
    LPSTR           lpstrFormName;
    LPWFSIDCCARDDATA *lppCardData;
} WFSIDCPARSEDATA, * LPWFSIDCPARSEDATA;

/*=====*/
/* IDC Message Structures */
/*=====*/

typedef struct _wfs_idc_track_event
{
    WORD            fwStatus;
    LPSTR           lpstrTrack;
    LPSTR           lpstrData;
} WFSIDCTRACKEVENT, * LPWFSIDCTRACKEVENT;

typedef struct _wfs_idc_card_act
{
    WORD            wAction;
    WORD            wPosition;
} WFSIDCCARDACT, * LPWFSIDCCARDACT;

/* restore alignment */
#pragma pack(pop)

#ifdef __cplusplus
} /*extern "C"*/
#endif

#endif /* __INC_XFSIDC__H */
```