

**CEN**

**CWA 16926-75**

**WORKSHOP**

February 2020

**AGREEMENT**

---

ICS 35.200; 35.240.15; 35.240.40

English version

**Extensions for Financial Services (XFS) interface  
specification Release 3.40 - Part 75: Card Dispenser Device  
Class Interface - Migration from version 3.30 (CWA 16926)  
to Version 3.40 (this CWA) - Programmer's Reference**

This CEN Workshop Agreement has been drafted and approved by a Workshop of representatives of interested parties, the constitution of which is indicated in the foreword of this Workshop Agreement.

The formal process followed by the Workshop in the development of this Workshop Agreement has been endorsed by the National Members of CEN but neither the National Members of CEN nor the CEN-CENELEC Management Centre can be held accountable for the technical content of this CEN Workshop Agreement or possible conflicts with standards or legislation.

This CEN Workshop Agreement can in no way be held as being an official standard developed by CEN and its Members.

This CEN Workshop Agreement is publicly available as a reference document from the CEN Members National Standard Bodies.

CEN members are the national standards bodies of Austria, Belgium, Bulgaria, Croatia, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and United Kingdom.



EUROPEAN COMMITTEE FOR STANDARDIZATION  
COMITÉ EUROPÉEN DE NORMALISATION  
EUROPÄISCHES KOMITEE FÜR NORMUNG

**CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels**

---

© 2020 CEN All rights of exploitation in any form and by any means reserved worldwide for CEN national Members.

Ref. No.:CWA 16926-75:2020 E

## Table of Contents

---

European Foreword.....	3
1. Migration Information.....	7
2. Card Dispensers .....	8
3. References .....	9
4. Info Commands .....	10
4.1 WFS_INF_CRD_STATUS .....	10
4.2 WFS_INF_CRD_CAPABILITIES .....	13
4.3 WFS_INF_CRD_CARD_UNIT_INFO .....	15
5. Execute Commands .....	17
5.1 WFS_CMD_CRD_DISPENSE_CARD .....	17
5.2 WFS_CMD_CRD_EJECT_CARD .....	18
5.3 WFS_CMD_CRD_RETAIN_CARD .....	19
5.4 WFS_CMD_CRD_RESET .....	20
5.5 WFS_CMD_CRD_SET_CARD_UNIT_INFO .....	21
5.6 WFS_CMD_CRD_SET_GUIDANCE_LIGHT .....	22
5.7 WFS_CMD_CRD_POWER_SAVE_CONTROL.....	24
5.8 WFS_CMD_CRD_SYNCHRONIZE_COMMAND .....	25
6. Events.....	26
6.1 WFS_SRVE_CRD_MEDIAREMOVED.....	26
6.2 WFS_SRVE_CRD_MEDIADETECTED .....	27
6.3 WFS_USRE_CRD_CARDUNITTHRESHOLD.....	28
6.4 WFS_SRVE_CRD_CARDUNITINFOCHANGED.....	29
6.5 WFS_EXEE_CRD_CARDUNITERROR.....	30
6.6 WFS_SRVE_CRD_DEVICEPOSITION.....	31
6.7 WFS_SRVE_CRD_POWER_SAVE_CHANGE .....	32
7. C-Header File .....	33

## European Foreword

---

This CEN Workshop Agreement has been developed in accordance with the CEN-CENELEC Guide 29 “CEN/CENELEC Workshop Agreements – The way to rapid consensus” and with the relevant provisions of CEN/CENELEC Internal Regulations - Part 2. It was approved by a Workshop of representatives of interested parties on 2019-10-08, the constitution of which was supported by CEN following several public calls for participation, the first of which was made on 1998-06-24. However, this CEN Workshop Agreement does not necessarily include all relevant stakeholders.

The final text of this CEN Workshop Agreement was provided to CEN for publication on 2019-12-12. The following organizations and individuals developed and approved this CEN Workshop Agreement:

- ATM Japan LTD
- AURIGA SPA
- BANK OF AMERICA
- CASHWAY TECHNOLOGY
- CHINAL ELECTRONIC FINANCIAL EQUIPMENT SYSTEM CO.
- CIMA SPA
- CLEAR2PAY SCOTLAND LIMITED
- DIEBOLD NIXDORF
- EASTERN COMMUNICATIONS CO. LTD – EASTCOM
- FINANZ INFORMATIK
- FUJITSU FRONTTECH LIMITED
- FUJITSU TECHNOLOGY
- GLORY LTD
- GRG BANKING EQUIPMENT HK CO LTD
- HESS CASH SYSTEMS GMBH & CO. KG
- HITACHI OMRON TS CORP.
- HYOSUNG TNS INC
- JIANGSU GUOQUANG ELECTRONIC INFORMATION TECHNOLOGY
- KAL
- KEBA AG
- NCR FSG
- NEC CORPORATION
- OKI ELECTRIC INDUSTRY SHENZHEN
- OKI ELECTRONIC INDUSTRY CO
- PERTO S/A

## **CWA 16926-75:2020 (E)**

- REINER GMBH & CO KG
- SALZBURGER BANKEN SOFTWARE
- SIGMA SPA
- TEB
- ZIJIN FULCRUM TECHNOLOGY CO

It is possible that some elements of this CEN/CWA may be subject to patent rights. The CEN-CENELEC policy on patent rights is set out in CEN-CENELEC Guide 8 “Guidelines for Implementation of the Common IPR Policy on Patents (and other statutory intellectual property rights based on inventions)”. CEN shall not be held responsible for identifying any or all such patent rights.

The Workshop participants have made every effort to ensure the reliability and accuracy of the technical and non-technical content of CWA 16926-75, but this does not guarantee, either explicitly or implicitly, its correctness. Users of CWA 16926-75 should be aware that neither the Workshop participants, nor CEN can be held liable for damages or losses of any kind whatsoever which may arise from its application. Users of CWA 16926-75 do so on their own responsibility and at their own risk.

The CWA is published as a multi-part document, consisting of:

Part 1: Application Programming Interface (API) - Service Provider Interface (SPI) - Programmer's Reference

Part 2: Service Classes Definition - Programmer's Reference

Part 3: Printer and Scanning Device Class Interface - Programmer's Reference

Part 4: Identification Card Device Class Interface - Programmer's Reference

Part 5: Cash Dispenser Device Class Interface - Programmer's Reference

Part 6: PIN Keypad Device Class Interface - Programmer's Reference

Part 7: Check Reader/Scanner Device Class Interface - Programmer's Reference

Part 8: Depository Device Class Interface - Programmer's Reference

Part 9: Text Terminal Unit Device Class Interface - Programmer's Reference

Part 10: Sensors and Indicators Unit Device Class Interface - Programmer's Reference

Part 11: Vendor Dependent Mode Device Class Interface - Programmer's Reference

Part 12: Camera Device Class Interface - Programmer's Reference

Part 13: Alarm Device Class Interface - Programmer's Reference

Part 14: Card Embossing Unit Device Class Interface - Programmer's Reference

Part 15: Cash-In Module Device Class Interface - Programmer's Reference

Part 16: Card Dispenser Device Class Interface - Programmer's Reference

Part 17: Barcode Reader Device Class Interface - Programmer's Reference

Part 18: Item Processing Module Device Class Interface - Programmer's Reference

Part 19: Biometrics Device Class Interface - Programmer's Reference

Parts 20 - 28: Reserved for future use.

Parts 29 through 47 constitute an optional addendum to this CWA. They define the integration between the SNMP standard and the set of status and statistical information exported by the Service Providers.

Part 29: XFS MIB Architecture and SNMP Extensions - Programmer's Reference

Part 30: XFS MIB Device Specific Definitions - Printer Device Class

Part 31: XFS MIB Device Specific Definitions - Identification Card Device Class

Part 32: XFS MIB Device Specific Definitions - Cash Dispenser Device Class

Part 33: XFS MIB Device Specific Definitions - PIN Keypad Device Class

- Part 34: XFS MIB Device Specific Definitions - Check Reader/Scanner Device Class
- Part 35: XFS MIB Device Specific Definitions - Depository Device Class
- Part 36: XFS MIB Device Specific Definitions - Text Terminal Unit Device Class
- Part 37: XFS MIB Device Specific Definitions - Sensors and Indicators Unit Device Class
- Part 38: XFS MIB Device Specific Definitions - Camera Device Class
- Part 39: XFS MIB Device Specific Definitions - Alarm Device Class
- Part 40: XFS MIB Device Specific Definitions - Card Embossing Unit Class
- Part 41: XFS MIB Device Specific Definitions - Cash-In Module Device Class
- Part 42: Reserved for future use.
- Part 43: XFS MIB Device Specific Definitions - Vendor Dependent Mode Device Class
- Part 44: XFS MIB Application Management
- Part 45: XFS MIB Device Specific Definitions - Card Dispenser Device Class
- Part 46: XFS MIB Device Specific Definitions - Barcode Reader Device Class
- Part 47: XFS MIB Device Specific Definitions - Item Processing Module Device Class
- Part 48: XFS MIB Device Specific Definitions - Biometrics Device Class
- Parts 49 - 60 are reserved for future use.
- Part 61: Application Programming Interface (API) - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Service Provider Interface (SPI) - Programmer's Reference
- Part 62: Printer and Scanning Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 63: Identification Card Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 64: Cash Dispenser Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 65: PIN Keypad Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 66: Check Reader/Scanner Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 67: Depository Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 68: Text Terminal Unit Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 69: Sensors and Indicators Unit Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 70: Vendor Dependent Mode Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 71: Camera Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 72: Alarm Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 73: Card Embossing Unit Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 74: Cash-In Module Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference
- Part 75: Card Dispenser Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference

## **CWA 16926-75:2020 (E)**

Part 76: Barcode Reader Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference

Part 77: Item Processing Module Device Class Interface - Migration from Version 3.30 (CWA 16926) to Version 3.40 (this CWA) - Programmer's Reference

In addition to these Programmer's Reference specifications, the reader of this CWA is also referred to a complementary document, called Release Notes. The Release Notes contain clarifications and explanations on the CWA specifications, which are not requiring functional changes. The current version of the Release Notes is available online from: [https://www.cen.eu/work/Sectors/Digital\\_society/Pages/WSXFS.aspx](https://www.cen.eu/work/Sectors/Digital_society/Pages/WSXFS.aspx).

The information in this document represents the Workshop's current views on the issues discussed as of the date of publication. It is provided for informational purposes only and is subject to change without notice. CEN makes no warranty, express or implied, with respect to this document.

## 1. Migration Information

---

XFS 3.40 has been designed to minimize backwards compatibility issues. This document highlights the changes made to the CRD device class between version 3.30 and 3.40, by highlighting the additions and deletions to the text.

## 2. Card Dispensers

---

This specification describes the functionality of the services provided by the Card Dispenser (CRD) device class under XFS, by defining the service-specific commands that can be issued, using the **WFSGetInfo**, **WFSAsyncGetInfo**, **WFSExecute** and **WFSAsyncExecute** functions.

A Card Dispenser is used to dispense a single card to a consumer from one or more bins. Most card dispensers also have the ability to retain a card to a bin.

### 3. References

---

---

1. XFS Application Programming Interface (API)/Service Provider Interface (SPI), Programmer's Reference Revision 3.40
--

2. XFS Identification Card Device Class Interface - Programmer's Reference, Revision 3.40
---

## 4. Info Commands

---

### 4.1 WFS\_INF\_CRD\_STATUS

---

**Description** This command is used to request status information for the device.

**Input Param** None.

**Output Param** LPWFSCRDSTATUS lpStatus;

```
typedef struct _wfs_crd_status
{
    WORD                fwDevice;
    WORD                fwDispenser;
    WORD                fwTransport;
    WORD                fwMedia;
    WORD                fwShutter;
    LPSTR               lpzszExtra;
    DWORD               dwGuidLights[WFS_CRD_GUIDLIGHTS_SIZE];
    WORD                wDevicePosition;
    USHORT              usPowerSaveRecoveryTime;
    WORD                wAntiFraudModule;
} WFS_CRD_STATUS, *LPWFSCRDSTATUS;
```

#### *fwDevice*

Specifies the state of the card dispensing device as one of the following flags:

Value	Meaning
WFS_CRD_DEVONLINE	The device is online (i.e. powered on and operable).
WFS_CRD_DEVOFFLINE	The device is offline (e.g. the operator has taken the device offline by turning a switch).
WFS_CRD_DEVPOWEROFF	The device is powered off or physically not connected.
WFS_CRD_DEVNODEVICE	There is no device intended to be there; e.g. this type of self service machine does not contain such a device or it is internally not configured.
WFS_CRD_DEVHWERROR	The device is inoperable due to a hardware error.
WFS_CRD_DEVUSERERROR	The device is present but a person is preventing proper device operation.
WFS_CRD_DEVBUSY	The device is busy and unable to process an execute command at this time.
WFS_CRD_DEVFRAUDATTEMPT	The device is present but is inoperable because it has detected a fraud attempt.
WFS_CRD_DEVPOTENTIALFRAUD	The device has detected a potential fraud attempt and is capable of remaining in service. In this case the application should make the decision as to whether to take the device offline.

#### *fwDispenser*

Specifies the state of the card units including all retain bins as one of the following flags:

Value	Meaning
WFS_CRD_DISPCUOK	All card units present are in a good state.
WFS_CRD_DISPCUSTATE	One or more of the card units is in a low, empty or inoperative condition. Items can still be dispensed from at least one of the card units.
WFS_CRD_DISPCUSTOP	Due to a card unit failure dispensing is impossible. No items can be dispensed because all of the card units are in an empty or inoperative condition.
WFS_CRD_DISPCUUNKNOWN	Due to a hardware error or other condition, the state of the card units cannot be determined.

*fwTransport*

Specifies the state of the transport mechanism as one of the following values:

Value	Meaning
WFS_CRD_TPOK	The transport is in a good state.
WFS_CRD_TPINOP	The transport is inoperative due to a hardware failure or media jam.
WFS_CRD_TPUNKNOWN	Due to a hardware error or other condition, the state of the transport cannot be determined.
WFS_CRD_TPNOTSUPPORTED	The physical device has no transport or transport state reporting is not supported.

*fwMedia*

Specifies the state of a card that may or may not be present in the device. A card becomes media when it is moved from a dispense card unit. It will be one of the following values:

Value	Meaning
WFS_CRD_MEDIAPRESENT	Media is present in the device, but not in the exiting position and not jammed.
WFS_CRD_MEDIANOTPRESENT	Media is not present in the device and not at the exiting position.
WFS_CRD_MEDIAJAMMED	Media is jammed in the device.
WFS_CRD_MEDIANOTSUPP	Capability to report media position is not supported by the device.
WFS_CRD_MEDIAUNKNOWN	The media state cannot be determined with the device in its current state.
WFS_CRD_MEDIAEXITING	Media is at the exit slot of the card dispenser unit.

*fwShutter*

Specifies the state of the shutter as one of the following flags:

Value	Meaning
WFS_CRD_SHTCLOSED	The shutter is closed.
WFS_CRD_SHTOPEN	The shutter is opened.
WFS_CRD_SHTJAMMED	The shutter is jammed.
WFS_CRD_SHTUNKNOWN	Due to a hardware error or other condition, the state of the shutter cannot be determined.
WFS_CRD_SHTNOTSUPPORTED	The physical device has no shutter or shutter state reporting is not supported.

*lpszExtra*

Pointer to a list of vendor-specific, or any other extended, information. The information is returned as a series of “*key=value*” strings so that it is easily extensible by Service Providers. Each string is null-terminated, with the final string terminating with two null characters. An empty list may be indicated by either a NULL pointer or a pointer to two consecutive null characters.

*dwGuidLights [...]*

Specifies the state of the guidance light indicators. A number of guidance light types are defined below. Vendor specific guidance lights are defined starting from the end of the array. The maximum guidance light index is WFS\_CRD\_GUIDLIGHTS\_MAX.

Specifies the state of the guidance light indicator as

WFS\_CRD\_GUIDANCE\_NOT\_AVAILABLE, WFS\_CRD\_GUIDANCE\_OFF or a combination of the following flags consisting of one type B, optionally one type C and optionally one type D.

Value	Meaning	Type
WFS_CRD_GUIDANCE_NOT_AVAILABLE	The status is not available.	A
WFS_CRD_GUIDANCE_OFF	The light is turned off.	A
WFS_CRD_GUIDANCE_SLOW_FLASH	The light is blinking slowly.	B
WFS_CRD_GUIDANCE_MEDIUM_FLASH	The light is blinking medium frequency.	B
WFS_CRD_GUIDANCE_QUICK_FLASH	The light is blinking quickly.	B

WFS_CRD_GUIDANCE_CONTINUOUS	The light is turned on continuous (steady).	B
WFS_CRD_GUIDANCE_RED	The light is red.	C
WFS_CRD_GUIDANCE_GREEN	The light is green.	C
WFS_CRD_GUIDANCE_YELLOW	The light is yellow.	C
WFS_CRD_GUIDANCE_BLUE	The light is blue.	C
WFS_CRD_GUIDANCE_CYAN	The light is cyan.	C
WFS_CRD_GUIDANCE_MAGENTA	The light is magenta.	C
WFS_CRD_GUIDANCE_WHITE	The light is white.	C
WFS_CRD_GUIDANCE_ENTRY	The light is in the entry state.	D
WFS_CRD_GUIDANCE_EXIT	The light is in the “exit” state.	D

*dwGuidLights [WFS\_CRD\_GUIDANCE\_CARDDISP]*

Specifies the state of the guidance light indicator on the card dispensing unit.

*wDevicePosition*

Specifies the device position. The device position value is independent of the *fwDevice* value, e.g. when the device position is reported as WFS\_CRD\_DEVICENOTINPOSITION, *fwDevice* can have any of the values defined above (including WFS\_CRD\_DEVONLINE or WFS\_CRD\_DEVOFFLINE). If the device is not in its normal operating position (i.e. WFS\_CRD\_DEVICEINPOSITION) then media may not be presented through the normal customer interface. This value is one of the following values:

Value	Meaning
WFS_CRD_DEVICEINPOSITION	The device is in its normal operating position, or is fixed in place and cannot be moved.
WFS_CRD_DEVICENOTINPOSITION	The device has been removed from its normal operating position.
WFS_CRD_DEVICEPOSUNKNOWN	Due to a hardware error or other condition, the position of the device cannot be determined.
WFS_CRD_DEVICEPOSNOTSUPP	The physical device does not have the capability of detecting the position.

*usPowerSaveRecoveryTime*

Specifies the actual number of seconds required by the device to resume its normal operational state from the current power saving mode. This value is zero if either the power saving mode has not been activated or no power save control is supported.

*wAntiFraudModule*

Specifies the state of the anti-fraud module as one of the following values:

Value	Meaning
WFS_CRD_AFMNOTSUPP	No anti-fraud module is available.
WFS_CRD_AFMOK	Anti-fraud module is in a good state and no foreign device is detected.
WFS_CRD_AFMINOP	Anti-fraud module is inoperable.
WFS_CRD_AFMDEVICEDETECTED	Anti-fraud module detected the presence of a foreign device.
WFS_CRD_AFMUNKNOWN	The state of the anti-fraud module cannot be determined.

**Error Codes** Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Comments** Applications which require or expect specific information to be present in the *lpszExtra* parameter may not be device or vendor-independent. If the CRD device is part of a compound device with an IDC device then a dispense to transport can allow the IDC interface to be used to read/write from the card.

In the case where communications with the device has been lost, the *fwDevice* field will report WFS\_CRD\_DEVPOWEROFF when the device has been removed or WFS\_CRD\_DEVHWERROR if the communications are unexpectedly lost. All other fields will report their status as unknown.

## 4.2 WFS\_INF\_CRD\_CAPABILITIES

---

**Description** This command is used to request device capability information.

**Input Param** None.

**Output Param** LPWFSCRDCAPS lpCaps;

```
typedef struct _wfs_crd_caps
{
    WORD                wClass;
    BOOL                bCompound;
    WORD                fwPowerOnOption;
    WORD                fwPowerOffOption;
    BOOL                bCardTakenSensor;
    WORD                fwDispenseTo;
    LPSTR               lpszExtra;
    DWORD               dwGuidLights[WFS_CRD_GUIDLIGHTS_SIZE];
    BOOL                bPowerSaveControl;
    BOOL                bAntiFraudModule;
    LPDWORD             lpdwSynchronizableCommands;
} WFSSCRDCAPS, *LPWFSCRDCAPS;
```

*wClass*

Specifies the logical service class as WFS\_SERVICE\_CLASS\_CRD.

*bCompound*

Specifies whether the logical device is part of a compound physical device.

*fwPowerOnOption*

Specifies the power-on capabilities of the device hardware, as one of the following flags; applicable only to motor driven ID card units.

Value	Meaning
WFS_CRD_NOACTION	No power on actions are supported by the device.
WFS_CRD_EJECT	The card will be ejected on power-on (or off, see <i>fwPowerOffOption</i> below).
WFS_CRD_RETAIN	The card will be retained on power-on (off).
WFS_CRD_EJECTTHENRETAIN	The card will be ejected for a specified time after power-on then retained if not taken. The time for which the card is ejected is vendor dependent.

*fwPowerOffOption*

Specifies the power-off capabilities of the device hardware, as one of the flags specified for *fwPowerOnOption*.

*bCardTakenSensor*

Specifies whether or not the card dispenser has the ability to detect when a card is taken from the exit slot by a user. TRUE means a sensor exists and the “card taken” condition can be detected. In this case a WFS\_SRVE\_CRD\_MEDIATAKEN event will be generated when the card is removed. If set to FALSE then no event will be generated.

*fwDispenseTo*

Specifies where a card will be dispensed to as a combination of the following flags:

Value	Meaning
WFS_CRD_DISPTO_CONSUMER	A dispensed card can be delivered to the exit slot for the consumer to take.
WFS_CRD_DISPTO_TRANSPORT	A dispensed card can be delivered into the transport mechanism. The application must use WFS_CMD_CRD_EJECT_CARD to deliver the card to the consumer.

*lpzExtra*

Pointer to a list of vendor-specific, or any other extended, information. The information is returned as a series of “*key=value*” strings so that it is easily extensible by Service Providers. Each string is null-terminated, with the final string terminating with two null characters. An empty list may be indicated by either a NULL pointer or a pointer to two consecutive null characters.

*dwGuidLights [...]*

Specifies which guidance lights are available. A number of guidance light types are defined below. Vendor specific guidance lights are defined starting from the end of the array. The maximum guidance light index is WFS\_CRD\_GUIDLIGHTS\_MAX.

In addition to supporting specific flash rates and colors, some guidance lights also have the capability to show directional movement representing “entry” and “exit”. The “entry” state gives the impressions of leading a user to place media into a device and would be used for insertion of card or media. The “exit” state gives the impression of ejection from a device to a user and would be used for retrieving card and media from the machine.

The elements of this array are specified as a combination of the following flags and indicate all of the possible flash rates (type B), colors (type C) and directions (type D) that the guidance light indicator is capable of handling. If the guidance light indicator only supports one color then no value of type C is returned. If the guidance light indicator does not support direction then no value of type D is returned. A value of WFS\_CRD\_GUIDANCE\_NOT\_AVAILABLE indicates that the device has no guidance light indicator or the device controls the light directly with no application control possible.

Value	Meaning	Type
WFS_CRD_GUIDANCE_NOT_AVAILABLE	There is no guidance light control available at this position.	A
WFS_CRD_GUIDANCE_OFF	The light can be off.	B
WFS_CRD_GUIDANCE_SLOW_FLASH	The light can blink slowly.	B
WFS_CRD_GUIDANCE_MEDIUM_FLASH	The light can blink medium frequency.	B
WFS_CRD_GUIDANCE_QUICK_FLASH	The light can blink quickly.	B
WFS_CRD_GUIDANCE_CONTINUOUS	The light can be continuous (steady).	B
WFS_CRD_GUIDANCE_RED	The light can be red.	C
WFS_CRD_GUIDANCE_GREEN	The light can be green.	C
WFS_CRD_GUIDANCE_YELLOW	The light can be yellow.	C
WFS_CRD_GUIDANCE_BLUE	The light can be blue.	C
WFS_CRD_GUIDANCE_CYAN	The light can be cyan.	C
WFS_CRD_GUIDANCE_MAGENTA	The light can be magenta.	C
WFS_CRD_GUIDANCE_WHITE	The light can be white.	C
WFS_CRD_GUIDANCE_ENTRY	The light is in the entry state.	D
WFS_CRD_GUIDANCE_EXIT	The light is in the “exit” state.	D

*dwGuidLights [WFS\_CRD\_GUIDANCE\_CARDDISP]*

Specifies whether the guidance light indicator on the card unit is available.

*bPowerSaveControl*

Specifies whether power saving control is available. This can either be TRUE if available or FALSE if not available.

*bAntiFraudModule*

Specifies whether the anti-fraud module is available. This can either be TRUE if available or FALSE if not available.

*lpdwSynchronizableCommands*

Pointer to a zero-terminated list of DWORDs which contains the execute command IDs that can be synchronized. If no execute command can be synchronized then this parameter will be NULL.

**Error Codes**

Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Comments**

Applications which require or expect specific information to be present in the *lpzExtra* parameter may not be device or vendor-independent. If the CRD device is part of a compound device with an IDC device then a dispense to transport can allow the IDC interface to be used to read/write from the card.

### 4.3 WFS\_INF\_CRD\_CARD\_UNIT\_INFO

---

**Description** This command is used to obtain information regarding the status and contents of the card units in the CRD.

**Counts**

The values of the following fields of the WFSCRDCARDUNIT

*ulCount*

*ulRetainCount*

are persistent software counts and therefore may not represent the actual number of items in the card unit.

Persistent values are maintained through power failures, open sessions, close session and system resets.

**Threshold Events**

The threshold event WFS\_USRE\_CRD\_CARDUNITTHRESHOLD can be triggered either by hardware sensors in the device or by the *ulCount* reaching the *ulThreshold* value.

The application can check if the device has this capability by querying the *bHardwareSensor* field of the card unit structure.

**Input Param** None.

**Output Param** LPWFSCRDCUINFO lpCardUnitInfo;

```
typedef struct _wfs_crd_cu_info
{
    USHORT                usCount;
    LPWFSCRDCARDUNIT     *lppList;
} WFSRDCUINFO, *LPWFSCRDCUINFO;
```

*usCount*

Specifies the number of card unit structures returned.

*lppList*

Pointer to an array of pointers to WFSCRDCARDUNIT structures:

```
typedef struct _wfs_crd_cardunit
{
    USHORT                usNumber;
    LPSTR                 lpszCardName;
    USHORT                usType;
    ULONG                 ulInitialCount;
    ULONG                 ulCount;
    ULONG                 ulRetainCount;
    ULONG                 ulThreshold;
    USHORT                usStatus;
    BOOL                  bHardwareSensor;
} WFSRDCARDUNIT, *LPWFSCRDCARDUNIT;
```

*usNumber*

Index number of the card unit structure. Each structure has a unique logical number starting with a value of one (1) for the first structure, and incrementing by one for each subsequent structure.

*lpszCardName*

An identifier which is used to identify the type of cards in the card unit.

*usType*

Type of card unit as one of the following values:

Value	Meaning
WFS_CRD_SUPPLYBIN	The card unit is a supply card unit.
WFS_CRD_RETAINBIN	The card unit is a retain card unit.

*ulInitialCount*

Initial number of items contained in the card unit. This value is persistent.

*ulCount*

The number of items inside the card unit plus any items from the card units not yet presented to the customer. This count is decremented when the items are either presented to the customer or retained. This count is incremented for a retain bin after a retain operation.

If this value reaches zero it will not decrement further but will remain at zero. This value is persistent.

*ulRetainCount*

The number of items from this card unit which are in the retain bin. This field is always zero for a retain bin. This value is persistent.

*ulThreshold*

When *ulCount* reaches this value the WFS\_USRE\_CRD\_CARDUNITTHRESHOLD threshold event will be generated. A WFS\_CRD\_STATCUHIGH threshold will be sent for WFS\_CRD\_RETAINBIN or WFS\_CRD\_STATCULOW for a WFS\_CRD\_SUPPLYBIN. If this value is non-zero then hardware sensors in the device do not trigger threshold events.

*usStatus*

Supplies the status of the card unit as one of the following values:

Value	Meaning
WFS_CRD_STATCUOK	The card supply or retain unit is in a good state.
WFS_CRD_STATCULOW	The card supply unit is almost empty.
WFS_CRD_STATCUEMPTY	The card supply unit is empty.
WFS_CRD_STATCUINOP	The card supply or retain unit is inoperative.
WFS_CRD_STATCUMISSING	The card supply or retain unit is missing.
WFS_CRD_STATCUHIGH	The retain card unit is almost full.
WFS_CRD_STATCUFULL	The retain card unit is full.
WFS_CRD_STATCUUNKNOWN	The status of the card unit cannot be determined.

*bHardwareSensor*

Specifies whether or not threshold events can be generated based on hardware sensors in the device. This applies to WFS\_CRD\_STATCULOW and WFS\_CRD\_STATCUHIGH thresholds only. If this value is TRUE then threshold events may be generated based on hardware sensors as opposed to counts. If *ulThreshold* is non zero then hardware triggers are ignored and software trigger/counters are used. A WFS\_CRD\_STATCUHIGH threshold will be sent for a retain bin or WFS\_CRD\_STATCULOW for a card supply unit. This field is read only.

**Error Codes** Only the generic error codes defined in [Ref. 1] can be generated by this command.

**Comments** None.

## 5. Execute Commands

---

### 5.1 WFS\_CMD\_CRD\_DISPENSE\_CARD

---

**Description** This command will attempt to move a card from the internal supply to a dispensable position. If the card is only dispensed to the transport then the command WFS\_CMD\_CRD\_EJECT\_CARD should be used to get the card in a position that the consumer can take it.

If the CRD Service Provider is a compound device with the IDC class, then when the card has been successfully dispensed and is in the transport it can be treated like any other inserted card on the IDC interface. For example, if the device has read/write capabilities the card can be written to and read from using the IDC commands.

**Input Param** LPWFSCRDDISPENSE lpDispense;

```
typedef struct _wfs_crd_dispense
{
    USHORT          usNumber;
    BOOL            bPresent;
} WFSSCRDDISPENSE, *LPWFSCRDDISPENSE;
```

*usNumber*

The number of the card unit from which the card should be dispensed. The number of the card unit is the *usNumber* returned from WFS\_INF\_CRD\_UNIT\_INFO.

*bPresent*

If this field is set to TRUE then the items will be moved to the exit slot, if it is FALSE the items will be moved to the transport. The *bPresent* flag will be ignored if the device cannot dispense to the transport.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_MEDIAJAM	The card is jammed in the transport.
WFS_ERR_CRD_DEVICE_OCCUPIED	There is already a card in the dispensing device. A second card cannot be dispensed.
WFS_ERR_CRD_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error.
WFS_ERR_CRD_CARDUNITERROR	There is a problem with a card unit. The WFS_EXEE_CRD_CARDUNITERROR execute event is posted with the details.
WFS_ERR_CRD_MEDIARETAINED	The dispense operation failed the card has been retained and the device is clear.

**Events** In addition to the generic events defined in [Ref. 1] the following event can be generated by this command.

Value	Meaning
WFS_EXEE_CRD_CARDUNITERROR	A card unit caused an error during a dispense operation.
WFS_USRE_CRD_CARDUNITTHRESHOLD	A card unit has reached a threshold.
WFS_SRVE_CRD_MEDIAREMOVED	The card has been taken by the user.

**Comments** None.

## 5.2 WFS\_CMD\_CRD\_EJECT\_CARD

---

**Description** This command only needs to be used if the card is not delivered all the way to the exit slot during a WFS\_CMD\_CRD\_DISPENSE\_CARD operation. An example of this would be for a compound device where the card is dispensed only to the transport for reading/writing to the magnetic stripe. After the card is read from and/or written to, the card can then be ejected to the exit for removal by the consumer.

**Input Param** None.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_MEDIAJAM	The card is jammed.
WFS_ERR_CRD_SHUTTERFAIL	The open of the shutter failed due to manipulation or hardware error.
WFS_ERR_CRD_NOMEDIA	No card is present.
WFS_ERR_CRD_MEDIARETAINED	The card has been retained during attempts to eject it. The device is clear and can be used.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command:

Value	Meaning
WFS_SRVE_CRD_MEDIAREMOVED	The card has been taken by the user.
WFS_USRE_CRD_CARDUNITTHRESHOLD	A card unit has reached a threshold.

**Comments** None.

### 5.3 WFS\_CMD\_CRD\_RETAIN\_CARD

---

**Description** The card is removed from its present position and stored in a retain bin. The card dispensing unit sends an event if the storage capacity of the retain bin is reached. If the storage capacity has already been reached, and the command cannot be executed then the card remains in its present position and a WFS\_ERR\_CRD\_RETAINBINFULL error is returned.

**Input Param** LPWFSCRDRETAINCARD lpRetainCard;

```
typedef struct _wfs_crd_retain_card
{
    USHORT          usNumber;
} WFSSCRDRETAINCARD, *LPWFSCRDRETAINCARD;
```

*usNumber*

The number of the retain bin that the card is to be retracted to. This corresponds to the *usNumber* returned by the WFS\_INF\_CRD\_CARD\_UNIT\_INFO command and must represent a retain bin.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_MEDIAJAM	The card is jammed.
WFS_ERR_CRD_NOMEDIA	There is no card to retain.
WFS_ERR_CRD_RETAINBINFULL	The retain bin is full; no more cards can be retained. The current card is still in the device.
WFS_ERR_CRD_CARDUNITERROR	A card unit caused an error.
WFS_ERR_CRD_INVALIDRETAINBIN	The retain bin specified in the <i>usNumber</i> input parameter is invalid.

**Events** In addition to the generic events defined in [Ref.1], the following events can be generated by this command:

Value	Meaning
WFS_USRE_CRD_CARDUNITTHRESHOLD	A card unit has reached a threshold.
WFS_SRVE_CRD_MEDIAREMOVED	The card has been taken by the user.

**Comments** If a retain request is received by a device with no retain capability, the WFS\_ERR\_UNSUPP\_COMMAND error is returned.

## 5.4 WFS\_CMD\_CRD\_RESET

---

**Description** This command is used by the application to perform a hardware reset which will attempt to return the CRD device to a known good state. This command does not over-ride a lock obtained by another application or service handle.

**Input Param** LPWFSCRDRESET lpResetIn;

```
typedef struct _wfs_crd_reset
{
    USHORT          usAction;
} WFS_CRDRESET, *LPWFSCRDRESET;
```

*usAction*

Specifies the action to be performed on any card found within the device as one of the following values:

Value	Meaning
WFS_CRD_EJECT	Eject any card found.
WFS_CRD_RETAIN	Retain any card found.
WFS_CRD_NOACTION	No action should be performed on any card found.

If the application does not wish to specify an action it can set *lpResetIn* to NULL. In this case the Service Provider will determine where to move the card.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_MEDIAJAM	A card is jammed. Operator intervention is required.
WFS_ERR_CRD_SHUTTERFAIL	The device is unable to open and close its shutter.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:

Value	Meaning
WFS_SRVE_CRD_MEDIADETECTED	This event is generated when media is detected during a reset.
WFS_USRE_CRD_CARDUNITTHRESHOLD	A card unit has reached a threshold.
WFS_SRVE_CRD_MEDIAREMOVED	The card has been taken by the user.

**Comments** None.

## 5.5 WFS\_CMD\_CRD\_SET\_CARD\_UNIT\_INFO

---

**Description** This command is used to adjust information regarding the contents of the card units present in the CRD. Some fields may be ignored by the Service Provider if the information can be obtained from the device. In some cases the fields that can be set is dependent on Service Provider configuration.

The following fields cannot be changed using this command.

*usNumber*  
*usType*  
*usStatus*  
*bHardwareSensor*

This command generates the service event WFS\_SRVE\_CRD\_CARDUNITINFOCHANGED to inform applications that the information for a card unit has been changed.

**Input Param** LPWFSCRDCUINFO lpCUInfo;

The WFSRDCUINFO structure is specified in the documentation of the WFS\_INF\_CRD\_CARD\_UNIT\_INFO command. This structure contains all of the card units reported by the WFSRDCUINFO command.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_INVALIDCARDUNIT	Invalid card unit.

**Events** In addition to the generic events defined in [Ref. 1], the following events can be generated as a result of this command:

Value	Meaning
WFS_USRE_CRD_CARDUNITTHRESHOLD	A card unit has reached a threshold or a threshold has been cleared.
WFS_SRVE_CRD_CARDUNITINFOCHANGED	A card unit was updated as a result of this command.

**Comments** None.

## 5.6 WFS\_CMD\_CRD\_SET\_GUIDANCE\_LIGHT

---

**Description** This command is used to set the status of the CRD guidance lights. This includes defining the flash rate, the color and a direction. When an application tries to use a color or direction that is not supported then the Service Provider will return the generic error WFS\_ERR\_UNSUPP\_DATA.

**Input Param** LPWFSCRDSETGUIDLIGHT lpSetGuidLight;

```
typedef struct _wfs_crd_set_guidlight
{
    WORD                wGuidLight;
    DWORD               dwCommand;
} WFS_CRDSETGUIDLIGHT, *LPWFSCRDSETGUIDLIGHT;
```

*wGuidLight*

Specifies the index of the guidance light to set as one of the values defined within the capabilities section.

*dwCommand*

Specifies the state of the guidance light indicator as WFS\_CRD\_GUIDANCE\_OFF or a combination of the following flags consisting of one type B, optionally one type C and optionally one type D. If no value of type C is specified then the default color is used. The Service Provider determines which color is used as the default color.

Value	Meaning	Type
WFS_CRD_GUIDANCE_OFF	The light indicator is turned off.	A
WFS_CRD_GUIDANCE_SLOW_FLASH	The light indicator is set to flash slowly.	B
WFS_CRD_GUIDANCE_MEDIUM_FLASH	The light indicator is set to flash medium frequency.	B
WFS_CRD_GUIDANCE_QUICK_FLASH	The light indicator is set to flash quickly.	B
WFS_CRD_GUIDANCE_CONTINUOUS	The light indicator is turned on continuously (steady).	B
WFS_CRD_GUIDANCE_RED	The light indicator color is set to red.	C
WFS_CRD_GUIDANCE_GREEN	The light indicator color is set to green.	C
WFS_CRD_GUIDANCE_YELLOW	The light indicator color is set to yellow.	C
WFS_CRD_GUIDANCE_BLUE	The light indicator color is set to blue.	C
WFS_CRD_GUIDANCE_CYAN	The light indicator color is set to cyan.	C
WFS_CRD_GUIDANCE_MAGENTA	The light indicator color is set to magenta.	C
WFS_CRD_GUIDANCE_WHITE	The light indicator color is set to white.	C
WFS_CRD_GUIDANCE_ENTRY	The light indicator is set to the entry state.	D
WFS_CRD_GUIDANCE_EXIT	The light is set to the exit state.	D

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_INVALID_PORT	An attempt to set a guidance light to a new value was invalid because the guidance light does not exist.

**Events** Only the generic events defined in [Ref. 1] can be generated by this command.

**Comments**

Guidance light support was added into the CRD primarily to support guidance lights for workstations where more than one instance of a CRD is present. The original CRD guidance light mechanism was not able to manage guidance lights for workstations with multiple CRDs. This command can also be used to set the status of the CRD guidance lights when only one instance of a CRD is present.

The slow and medium flash rates must not be greater than 2.0 Hz. It should be noted that in order to comply with American Disabilities Act guidelines only a slow or medium flash rate must be used.

## 5.7 WFS\_CMD\_CRD\_POWER\_SAVE\_CONTROL

---

<b>Description</b>	<p>This command activates or deactivates the power-saving mode.</p> <p>If the Service Provider receives another execute command while in power saving mode, the Service Provider automatically exits the power saving mode, and executes the requested command. If the Service Provider receives an information command while in power saving mode, the Service Provider will not exit the power saving mode.</p>						
<b>Input Param</b>	<p>LPWFSCRDPWERSAVECONTROL lpPowerSaveControl;</p> <pre>typedef struct _wfs_crd_power_save_control {     USHORT                usMaxPowerSaveRecoveryTime; } WFS_CRD_POWER_SAVE_CONTROL, *LPWFSCRDPWERSAVECONTROL;</pre> <p><i>usMaxPowerSaveRecoveryTime</i> Specifies the maximum number of seconds in which the device must be able to return to its normal operating state when exiting power save mode. The device will be set to the highest possible power save mode within this constraint. If <i>usMaxPowerSaveRecoveryTime</i> is set to zero then the device will exit the power saving mode.</p>						
<b>Output Param</b>	None.						
<b>Error Codes</b>	<p>In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:</p> <table border="0"> <thead> <tr> <th style="text-align: left; border-bottom: 1px solid black;">Value</th> <th style="text-align: left; border-bottom: 1px solid black;">Meaning</th> </tr> </thead> <tbody> <tr> <td style="vertical-align: top;">WFS_ERR_CRD_POWERSAVETOOSHORT</td> <td style="vertical-align: top;">The power saving mode has not been activated because the device is not able to resume from the power saving mode within the specified <i>usMaxPowerSaveRecoveryTime</i> value.</td> </tr> <tr> <td style="vertical-align: top;">WFS_ERR_CRD_POWERSAVEMEDIAPRESENT</td> <td style="vertical-align: top;">The power saving mode has not been activated because media is present inside the device.</td> </tr> </tbody> </table>	Value	Meaning	WFS_ERR_CRD_POWERSAVETOOSHORT	The power saving mode has not been activated because the device is not able to resume from the power saving mode within the specified <i>usMaxPowerSaveRecoveryTime</i> value.	WFS_ERR_CRD_POWERSAVEMEDIAPRESENT	The power saving mode has not been activated because media is present inside the device.
Value	Meaning						
WFS_ERR_CRD_POWERSAVETOOSHORT	The power saving mode has not been activated because the device is not able to resume from the power saving mode within the specified <i>usMaxPowerSaveRecoveryTime</i> value.						
WFS_ERR_CRD_POWERSAVEMEDIAPRESENT	The power saving mode has not been activated because media is present inside the device.						
<b>Events</b>	<p>In addition to the generic events defined in [Ref. 1], the following events can be generated by this command:</p> <table border="0"> <thead> <tr> <th style="text-align: left; border-bottom: 1px solid black;">Value</th> <th style="text-align: left; border-bottom: 1px solid black;">Meaning</th> </tr> </thead> <tbody> <tr> <td style="vertical-align: top;">WFS_SRVE_CRD_POWER_SAVE_CHANGE</td> <td style="vertical-align: top;">The power save recovery time has changed.</td> </tr> </tbody> </table>	Value	Meaning	WFS_SRVE_CRD_POWER_SAVE_CHANGE	The power save recovery time has changed.		
Value	Meaning						
WFS_SRVE_CRD_POWER_SAVE_CHANGE	The power save recovery time has changed.						
<b>Comments</b>	None.						

## 5.8 WFS\_CMD\_CRD\_SYNCHRONIZE\_COMMAND

---

**Description** This command is used to reduce response time of a command (e.g. for synchronization with display) as well as to synchronize actions of the different device classes. This command is intended to be used only on hardware which is capable of synchronizing functionality within a single device class or with other device classes.

The list of execute commands which this command supports for synchronization is retrieved in the *lpdwSynchronizableCommands* parameter of the WFS\_INF\_CRD\_CAPABILITIES.

This command is optional, i.e. any other command can be called without having to call it in advance. Any preparation that occurs by calling this command will not affect any other subsequent command. However, any subsequent execute command other than the one that was specified in the *dwCommand* input parameter will execute normally and may invalidate the pending synchronization. In this case the application should call the WFS\_CMD\_CRD\_SYNCHRONIZE\_COMMAND again in order to start a synchronization.

**Input Param** LPWFSCRDSYNCHRONIZECOMMAND lpSynchronizeCommand;

```
typedef struct _wfs_crd_synchronize_command
{
    DWORD                dwCommand;
    LPVOID               lpCmdData;
} WFSSCRDSYNCHRONIZECOMMAND, *LPWFSCRDSYNCHRONIZECOMMAND;
```

*dwCommand*

The command ID of the command to be synchronized and executed next.

*lpCmdData*

Pointer to data or a data structure that represents the parameter that is normally associated with the command that is specified in *dwCommand*. For example, if *dwCommand* is WFS\_CMD\_CRD\_DISPENSE then *lpCmdData* will point to a WFSCRDDISPENSE structure. This parameter can be NULL if no command input parameter is needed or if this detail is not needed to synchronize for the command.

It will be device-dependent whether the synchronization is effective or not in the case where the application synchronizes for a command with this command specifying a parameter but subsequently executes the synchronized command with a different parameter. This case should not result in an error; however, the preparation effect could be different from what the application expects. The application should, therefore, make sure to use the same parameter between *lpCmdData* of this command and the subsequent corresponding execute command.

**Output Param** None.

**Error Codes** In addition to the generic error codes defined in [Ref. 1], the following error codes can be generated by this command:

Value	Meaning
WFS_ERR_CRD_COMMANDUNSUPP	The command specified in the <i>dwCommand</i> field is not supported by the Service Provider.
WFS_ERR_CRD_SYNCHRONIZEUNSUPP	The preparation for the command specified in the <i>dwCommand</i> with the parameter specified in the <i>lpCmdData</i> is not supported by the Service Provider.

**Events** Only the generic events defined in [Ref. 1] can be generated by this command.

**Comments** For sample flows of this synchronization see the [Ref 1] Appendix C.

## 6. Events

---

### 6.1 WFS\_SRVE\_CRD\_MEDIAREMOVED

---

<b>Description</b>	This event is sent when the media is taken from the exit slot.
<b>Event Param</b>	None.
<b>Comments</b>	This event occurs after the completion of a function that ejects the media, it is not an execute event.

## 6.2 WFS\_SRVE\_CRD\_MEDIADETECTED

---

**Description** This event is generated when media is detected in the device during a reset operation.

**Event Param** LPWFSCRDMEDIADETECTED lpMediaDetected;

```
typedef struct _wfs_crd_media_detected
{
    WORD                wPosition;
    USHORT              usNumber;
} WFS_CRD_MEDIADETECTED, *LPWFSCRDMEDIADETECTED;
```

*wPosition*

Specifies the media position after the reset operation, as one of the following values:

Value	Meaning
WFS_CRD_MEDIARETAINED	The media was retained during the reset operation.
WFS_CRD_MEDIAPRESENT	The media is present somewhere in the transport.
WFS_CRD_MEDIAEXITING	The media is in the exit slot.
WFS_CRD_MEDIAJAMMED	The media is jammed in the device.
WFS_CRD_MEDIAUNKNOWN	The media is in an unknown position.

*usNumber*

Number of the retain bin the media was retained to. This number has to be between one and the number of bins supported by this device. It is only relevant if *wPosition* equals WFS\_CRD\_MEDIARETAINED.

**Comments** None.

### 6.3 WFS\_USRE\_CRD\_CARDUNITTHRESHOLD

---

<b>Description</b>	This user event is generated when a threshold condition has occurred in one of the card units.
<b>Event Param</b>	LPWFSCRDCARDUNIT lpCardUnit;  <i>lpCardUnit</i> Pointer to a WFSCRDCARDUNIT structure describing the card unit on which the threshold condition occurred. See <i>lpCardUnit-&gt;usStatus</i> for the current status. For a description of the WFSCRDCARDUNIT structure see the definition of the WFS_INF_CRD_CARD_UNIT_INFO command.
<b>Comments</b>	None.

## 6.4 WFS\_SRVE\_CRD\_CARDUNITINFOCHANGED

---

<b>Description</b>	This service event is generated when information about a card unit has changed. This event will also be posted on successful completion of the following commands:  WFS_CMD_CRD_SET_CARD_UNIT_INFO
<b>Event Param</b>	LPWFSCRDCARDUNIT lpCardUnit;  <i>lpCardUnit</i> Pointer to the changed card unit structure. For a description of the WFSCRDCARDUNIT structure see the definition of the WFS_INF_CRD_CARD_UNIT_INFO command.
<b>Comments</b>	None.

## 6.5 WFS\_EXEE\_CRD\_CARDUNITERROR

---

**Description** This execute event is generated if there is a problem with a card unit during a dispense operation.

**Event Param** LPWFSCRDCUERROR lpCardUnitError;

```
typedef struct _wfs_crd_cu_error
{
    WORD wFailure;
    LPWFSCRDCARDUNIT lpCardUnit;
} WFSRDCUERROR, *LPWFSCRDCUERROR;
```

*wFailure*

Specifies the kind of failure that occurred in the card unit. Values are:

Value	Meaning
WFS_CRD_CARDUNITEMPTY	Specified card unit is empty.
WFS_CRD_CARDUNITERROR	Specified card unit has malfunctioned.
WFS_CRD_CARDUNITINVALID	Specified card unit ID is invalid.

*lpCardUnit*

Pointer to the card unit structure that caused the problem. The WFSRDCARDUNIT structure is defined in the documentation of the WFS\_INF\_CRD\_CARD\_UNIT\_INFO command. It is possible that this pointer may be NULL if the *wFailure* field is WFS\_CRD\_CARDUNITINVALID.

**Comments** None.

## 6.6 WFS\_SRVE\_CRD\_DEVICEPOSITION

---

**Description** This service event reports that the device has changed its position status.

**Event Param** LPWFSCRDDEVICEPOSITION lpDevicePosition;

```
typedef struct _wfs_crd_device_position
{
    WORD wPosition;
} WFS_CRD_DEVICEPOSITION, *LPWFSCRDDEVICEPOSITION;
```

*wPosition*

Position of the device as one of the following values:

Value	Meaning
WFS_CRD_DEVICEINPOSITION	The device is in its normal operating position.
WFS_CRD_DEVICENOTINPOSITION	The device has been removed from its normal operating position.
WFS_CRD_DEVICEPOSUNKNOWN	The position of the device cannot be determined.

**Comments** None.

## 6.7 WFS\_SRVE\_CRD\_POWER\_SAVE\_CHANGE

---

<b>Description</b>	This service event specifies that the power save recovery time has changed.
<b>Event Param</b>	<p>LPWFSCRDPWERSAVECHANGE lpPowerSaveChange;</p> <pre>typedef struct _wfs_crd_power_save_change {     USHORT                usPowerSaveRecoveryTime; } WFS_CRD_POWER_SAVE_CHANGE, *LPWFSCRDPWERSAVECHANGE;</pre> <p><i>usPowerSaveRecoveryTime</i> Specifies the actual number of seconds required by the device to resume its normal operational state. This value is zero if the device exited the power saving mode.</p>
<b>Comments</b>	If another device class compound with this device enters into a power saving mode this device will automatically enter into the same power saving mode and this event will be generated.

## 7. C-Header File

---

```

/*****
*
* xfscrd.h      XFS - Card Dispenser (CRD) definitions
*
*              Version 3.40   (December 6 2019)
*
*****/

#ifndef __INC_XFSCRD_H
#define __INC_XFSCRD_H

#ifdef __cplusplus
extern "C" {
#endif

#include <xfsap.h>

/* be aware of alignment */
#pragma pack(push,1)

/* values of WFSCRDCAPS.wClass */

#define WFS_SERVICE_CLASS_CRD                (14)
#define WFS_SERVICE_CLASS_VERSION_CRD      (0x2803) /* Version 3.40 */
#define WFS_SERVICE_CLASS_NAME_CRD        "CRD"

#define CRD_SERVICE_OFFSET                  (WFS_SERVICE_CLASS_CRD * 100)

/* CRD Info Commands */

#define WFS_INF_CRD_STATUS                   (CRD_SERVICE_OFFSET + 1)
#define WFS_INF_CRD_CAPABILITIES            (CRD_SERVICE_OFFSET + 2)
#define WFS_INF_CRD_CARD_UNIT_INFO         (CRD_SERVICE_OFFSET + 3)

/* CRD Execute Commands */

#define WFS_CMD_CRD_DISPENSE_CARD           (CRD_SERVICE_OFFSET + 1)
#define WFS_CMD_CRD_EJECT_CARD             (CRD_SERVICE_OFFSET + 2)
#define WFS_CMD_CRD_RETAIN_CARD            (CRD_SERVICE_OFFSET + 3)
#define WFS_CMD_CRD_RESET                  (CRD_SERVICE_OFFSET + 4)
#define WFS_CMD_CRD_SET_GUIDANCE_LIGHT     (CRD_SERVICE_OFFSET + 5)
#define WFS_CMD_CRD_SET_CARD_UNIT_INFO    (CRD_SERVICE_OFFSET + 6)
#define WFS_CMD_CRD_POWER_SAVE_CONTROL    (CRD_SERVICE_OFFSET + 7)
#define WFS_CMD_CRD_SYNCHRONIZE_COMMAND    (CRD_SERVICE_OFFSET + 8)

/* CRD Events */

#define WFS_SRVE_CRD_MEDIAREMOVED          (CRD_SERVICE_OFFSET + 1)
#define WFS_SRVE_CRD_CARDUNITINFOCHANGED  (CRD_SERVICE_OFFSET + 2)
#define WFS_SRVE_CRD_MEDIADETEECTED       (CRD_SERVICE_OFFSET + 3)
#define WFS_USRE_CRD_CARDUNITTHRESHOLD    (CRD_SERVICE_OFFSET + 4)
#define WFS_EXEE_CRD_CARDUNITERROR        (CRD_SERVICE_OFFSET + 5)
#define WFS_SRVE_CRD_DEVICEPOSITION        (CRD_SERVICE_OFFSET + 6)
#define WFS_SRVE_CRD_POWER_SAVE_CHANGE    (CRD_SERVICE_OFFSET + 7)

/* values of WFSCRDSTATUS.fwDevice */

#define WFS_CRD_DEVONLINE                  WFS_STAT_DEVONLINE
#define WFS_CRD_DEVOFFLINE                 WFS_STAT_DEVOFFLINE
#define WFS_CRD_DEVPOWEROFF                WFS_STAT_DEVPOWEROFF
#define WFS_CRD_DEVNODEVICE                WFS_STAT_DEVNODEVICE
#define WFS_CRD_DEVHWERROR                 WFS_STAT_DEVHWERROR
#define WFS_CRD_DEVUSERERROR               WFS_STAT_DEVUSERERROR
#define WFS_CRD_DEVBUSY                    WFS_STAT_DEVBUSY
#define WFS_CRD_DEVFRAUDATTEMPT           WFS_STAT_DEVFRAUDATTEMPT
#define WFS_CRD_DEVPOTENTIALFRAUD         WFS_STAT_DEVPOTENTIALFRAUD

```

## CWA 16926-75:2020 (E)

```
/* values of WFSCRDSTATUS.fwDispenser */

#define WFS_CRD_DISPCUOK (0)
#define WFS_CRD_DISPCUSTATE (1)
#define WFS_CRD_DISPCUSTOP (2)
#define WFS_CRD_DISPCUUNKNOWN (3)

/* values of WFSCRDSTATUS.fwMedia,
   WFSCRDRETAINCARD.fwPosition, and
   WFSCRDMEDIADETECTED.wPosition */

#define WFS_CRD_MEDIAPRESENT (1)
#define WFS_CRD_MEDIANOTPRESENT (2)
#define WFS_CRD_MEDIAJAMMED (3)
#define WFS_CRD_MEDIANOTSUPP (4)
#define WFS_CRD_MEDIAUNKNOWN (5)
#define WFS_CRD_MEDIAEXITING (6)
#define WFS_CRD_MEDIARETAINED (7)

/* values of WFSCRDSTATUS.fwTransport */

#define WFS_CRD_TPOK (0)
#define WFS_CRD_TPINOP (1)
#define WFS_CRD_TPUNKNOWN (2)
#define WFS_CRD_TPNOTSUPPORTED (3)

/* Size and max index of dwGuidLights array */

#define WFS_CRD_GUIDLIGHTS_SIZE (32)
#define WFS_CRD_GUIDLIGHTS_MAX (WFS_CRD_GUIDLIGHTS_SIZE - 1)

/* Indices of WFSCRDSTATUS.dwGuidLights [...]
   WFSCRDCAPS.dwGuidLights [...] */

#define WFS_CRD_GUIDANCE_CARDDISP (0)

/* Values of WFSCRDSTATUS.dwGuidLights [...]
   WFSCRDCAPS.dwGuidLights [...] */

#define WFS_CRD_GUIDANCE_NOT_AVAILABLE (0x00000000)
#define WFS_CRD_GUIDANCE_OFF (0x00000001)
#define WFS_CRD_GUIDANCE_SLOW_FLASH (0x00000004)
#define WFS_CRD_GUIDANCE_MEDIUM_FLASH (0x00000008)
#define WFS_CRD_GUIDANCE_QUICK_FLASH (0x00000010)
#define WFS_CRD_GUIDANCE_CONTINUOUS (0x00000080)
#define WFS_CRD_GUIDANCE_RED (0x00000100)
#define WFS_CRD_GUIDANCE_GREEN (0x00000200)
#define WFS_CRD_GUIDANCE_YELLOW (0x00000400)
#define WFS_CRD_GUIDANCE_BLUE (0x00000800)
#define WFS_CRD_GUIDANCE_CYAN (0x00001000)
#define WFS_CRD_GUIDANCE_MAGENTA (0x00002000)
#define WFS_CRD_GUIDANCE_WHITE (0x00004000)
#define WFS_CRD_GUIDANCE_ENTRY (0x00100000)
#define WFS_CRD_GUIDANCE_EXIT (0x00200000)

/* values of WFSCRDSTATUS.wDevicePosition
   WFSCRDDEVICEPOSITION.wPosition */

#define WFS_CRD_DEVICEINPOSITION (0)
#define WFS_CRD_DEVICEINNOTINPOSITION (1)
#define WFS_CRD_DEVICEPOSUNKNOWN (2)
#define WFS_CRD_DEVICEPOSNOTSUPP (3)

/*values of WFSCRDCAPS.fwDispenseTo */

#define WFS_CRD_DISPTO_CONSUMER (0x0001)
#define WFS_CRD_DISPTO_TRANSPORT (0x0002)

/*values of WFSCRDCARDUNIT.usStatus */
```

```

#define WFS_CRD_STATCUOK (0)
#define WFS_CRD_STATCULOW (1)
#define WFS_CRD_STATCUEMPTY (2)
#define WFS_CRD_STATCUINOP (3)
#define WFS_CRD_STATCUMISSING (4)
#define WFS_CRD_STATCUHIGH (5)
#define WFS_CRD_STATCUFULL (6)
#define WFS_CRD_STATCUUNKNOWN (7)

/*values of WFSRDCARDUNIT.usType */

#define WFS_CRD_SUPPLYBIN (1)
#define WFS_CRD_RETAINBIN (2)

/* values of WFSRDCSTATUS.fwShutter */

#define WFS_CRD_SHTCLOSED (0)
#define WFS_CRD_SHTOPEN (1)
#define WFS_CRD_SHTJAMMED (2)
#define WFS_CRD_SHTUNKNOWN (3)
#define WFS_CRD_SHTNOTSUPPORTED (4)

/* values of WFSRDCAPS.fwPowerOnOption,
WFSRDCAPS.fwPowerOffOption,
WFSRCDRESET.usAction */

#define WFS_CRD_NOACTION (1)
#define WFS_CRD_EJECT (2)
#define WFS_CRD_RETAIN (3)
#define WFS_CRD_EJECTTHENRETAIN (4)

/*values of WFSRDCUERROR.wFailure */

#define WFS_CRD_CARDUNITEMPTY (1)
#define WFS_CRD_CARDUNITERROR (2)
#define WFS_CRD_CARDUNITINVALID (3)

/* values of WFSRDCSTATUS.wAntiFraudModule */

#define WFS_CRD_AFMNOTSUPP (0)
#define WFS_CRD_AFMOK (1)
#define WFS_CRD_AFMINOP (2)
#define WFS_CRD_AFMDEVICEDETECTED (3)
#define WFS_CRD_AFMUNKNOWN (4)

/* XFS CRD Errors */

#define WFS_ERR_CRD_MEDIAJAM (- (CRD_SERVICE_OFFSET + 0))
#define WFS_ERR_CRD_NOMEDIA (- (CRD_SERVICE_OFFSET + 1))
#define WFS_ERR_CRD_MEDIARETAINED (- (CRD_SERVICE_OFFSET + 2))
#define WFS_ERR_CRD_RETAINBINFULL (- (CRD_SERVICE_OFFSET + 3))
#define WFS_ERR_CRD_SHUTTERFAIL (- (CRD_SERVICE_OFFSET + 4))
#define WFS_ERR_CRD_DEVICE_OCCUPIED (- (CRD_SERVICE_OFFSET + 5))
#define WFS_ERR_CRD_CARDUNITERROR (- (CRD_SERVICE_OFFSET + 6))
#define WFS_ERR_CRD_INVALIDCARDUNIT (- (CRD_SERVICE_OFFSET + 7))
#define WFS_ERR_CRD_INVALID_PORT (- (CRD_SERVICE_OFFSET + 8))
#define WFS_ERR_CRD_INVALIDRETAINBIN (- (CRD_SERVICE_OFFSET + 9))
#define WFS_ERR_CRD_POWERSAVETOOSHORT (- (CRD_SERVICE_OFFSET + 10))
#define WFS_ERR_CRD_POWERSAVEMEDIAPRESENT (- (CRD_SERVICE_OFFSET + 11))
#define WFS_ERR_CRD_COMMANDUNSUPP (- (CRD_SERVICE_OFFSET + 12))
#define WFS_ERR_CRD_SYNCHRONIZEUNSUPP (- (CRD_SERVICE_OFFSET + 13))

/*=====*/
/* CRD Info Command Structures and variables */
/*=====*/

typedef struct _wfs_crd_status
{

```

## CWA 16926-75:2020 (E)

```
WORD          fwDevice;
WORD          fwDispenser;
WORD          fwTransport;
WORD          fwMedia;
WORD          fwShutter;
LPSTR         lpszExtra;
DWORD        dwGuidLights[WFS_CRD_GUIDLIGHTS_SIZE];
WORD          wDevicePosition;
USHORT        usPowerSaveRecoveryTime;
WORD          wAntiFraudModule;
} WFS CRDSTATUS, *LPWFS CRDSTATUS;

typedef struct _wfs_crd_caps
{
    WORD          wClass;
    BOOL          bCompound;
    WORD          fwPowerOnOption;
    WORD          fwPowerOffOption;
    BOOL          bCardTakenSensor;
    WORD          fwDispenseTo;
    LPSTR         lpszExtra;
    DWORD        dwGuidLights[WFS_CRD_GUIDLIGHTS_SIZE];
    BOOL          bPowerSaveControl;
    BOOL          bAntiFraudModule;
    LPDWORD       lpdwSynchronizableCommands;
} WFS CRDCAPS, *LPWFS CRDCAPS;

typedef struct _wfs_crd_cardunit
{
    USHORT        usNumber;
    LPSTR         lpszCardName;
    USHORT        usType;
    ULONG        ulInitialCount;
    ULONG        ulCount;
    ULONG        ulRetainCount;
    ULONG        ulThreshold;
    USHORT        usStatus;
    BOOL          bHardwareSensor;
} WFS CRDCARDUNIT, *LPWFS CRDCARDUNIT;

typedef struct _wfs_crd_cu_info
{
    USHORT        usCount;
    LPWFS CRDCARDUNIT *lppList;
} WFS CRDCUINFO, *LPWFS CRDCUINFO;

/*=====*/
/* CRD Execute Command Structures */
/*=====*/

typedef struct _wfs_crd_dispense
{
    USHORT        usNumber;
    BOOL          bPresent;
} WFS CRDDISPENSE, *LPWFS CRDDISPENSE;

typedef struct _wfs_crd_retain_card
{
    USHORT        usNumber;
} WFS CRDRETAINCARD, *LPWFS CRDRETAINCARD;

typedef struct _wfs_crd_reset
{
    USHORT        usAction;
} WFS CRDRESET, *LPWFS CRDRESET;

typedef struct _wfs_crd_set_guidlight
{
    WORD          wGuidLight;
    DWORD        dwCommand;
}
```

```

} WFSCRDSETGUIDLIGHT, *LPWFSCRDSETGUIDLIGHT;

typedef struct _wfs_crd_power_save_control
{
    USHORT                usMaxPowerSaveRecoveryTime;
} WFSCRDPOWERSAVECONTROL, *LPWFSCRDPOWERSAVECONTROL;

typedef struct _wfs_crd_synchronize_command
{
    DWORD                dwCommand;
    LPVOID                lpCmdData;
} WFSCRDSYNCHRONIZECOMMAND, *LPWFSCRDSYNCHRONIZECOMMAND;

/*=====*/
/* CRD Message Structures */
/*=====*/

typedef struct _wfs_crd_media_detected
{
    WORD                wPosition;
    USHORT                usNumber;
} WFSCRDMEDIADETECTED, *LPWFSCRDMEDIADETECTED;

typedef struct _wfs_crd_cu_error
{
    WORD                wFailure;
    LPWFSCRDCARDUNIT lpCardUnit;
} WFSCRDCUERROR, *LPWFSCRDCUERROR;

typedef struct _wfs_crd_device_position
{
    WORD                wPosition;
} WFSCRDDEVICEPOSITION, *LPWFSCRDDEVICEPOSITION;

typedef struct _wfs_crd_power_save_change
{
    USHORT                usPowerSaveRecoveryTime;
} WFSCRDPOWERSAVECHANGE, *LPWFSCRDPOWERSAVECHANGE;

/* restore alignment */
#pragma pack(pop)

#ifdef __cplusplus
} /*extern "C"*/
#endif

#endif /* __INC_XFSCRD__H */

```